

Spatially Resolved Infrared Radiofluorescence: Single-grain K-feldspar Dating using CCD Imaging

Dirk Mittelstraß¹ and Sebastian Kreutzer^{2,3}

¹Independent Researcher, Berthelsdorfer Str. 13, 09599 Freiberg, Germany

²Geography & Earth Sciences, Aberystwyth University, Wales, United Kingdom

³IRAMAT-CRP2A, UMR 5060, CNRS-Université Bordeaux Montaigne, Pessac, France

Correspondence: Dirk Mittelstraß (dirk.mittelstrass@luminescence.de) for technical questions and Sebastian Kreutzer (sebastian.kreutzer@aber.ac.uk) for questions on the experiments.

Abstract. The success of luminescence dating as a chronological tool in Quaternary science builds upon innovative methodological approaches, providing new insights into past landscapes. Infrared radiofluorescence (IR-RF) on K-feldspar is such an innovative method already introduced two decades ago. IR-RF promises considerable extended temporal range and a simple measurement protocol, with more dating applications published recently. To date, all applications use multi-grain measure-

5 ments. Herein, we take the next step by enabling IR-RF measurements on a single grain level. Our contribution introduces spatially resolved infrared radiofluorescence (SR IR-RF) on K-feldspars and intends to make SR IR-RF broadly accessible as a geochronological tool. In the first part of the manuscript, we detail equipment, CCD camera settings and software needed to perform and analyse SR IR-RF measurements. We use a newly developed *ImageJ* macro to process the image data, identify IR-

RF emitting grains and obtain single-grain IR-RF signal curves. For subsequent analysis, we apply the statistical programming 10 environment *R* and the package 'Luminescence'. In the second part of the manuscript, we test SR IR-RF on two K-feldspar samples. One sample was irradiated artificially; the other sample received a natural dose. The artificially irradiated sample renders results, indistinguishable from conventional IR-RF measurements with the photomultiplier tube. The natural sample seems to overestimate the expected dose by ca 50% on average. However, it also shows a lower dose component resulting in ages consistent with the same sample's quartz fraction. Our experiments also revealed an unstable signal background due 15 to our cameras' degenerated cooling system. Besides this technical issue specific to the system we used, SR IR-RF is ready for application. Our contribution provides guidance and software tools for methodological and applied luminescence(-dating) studies on single grain feldspars using radiofluorescence.

1 Introduction

During the last two decades of advances in luminescence-based chronologies, two promising developments stand out but

Deleted: *Copyright statement.* The attached software is distributed under GPL-3 licence conditions and the attached datasets make use of the Creative Commons license (CC-BY-NC). The manuscript is distributed under the licence conditions of the publisher. ¶
20

20 somehow never took off: (1) Spatially resolved (SR) detection of optical- and thermoluminescence signals and (2) infrared radiofluorescence (IR-RF) of potassium feldspar (K-feldspar). Our perception is that the most significant obstacles in both approaches lie in imperfections of the available instrumentation and the complexity of the data analysis.

Although aware of this, we draw upon both developments, SR and IR-RF, and present a new approach: Spatially resolved infrared-radiofluorescence (henceforth: SR IR-RF) for measuring K-feldspar on a single grain level. This manuscript has two 25 parts. After a brief literature review, the first part will outline the technical aspects and the data analysis methods. The second part will test and apply the developed approach.

As it concerns our manuscript's technical part, we attempt to summarise our work on SR IR-RF of K-feldspar carried out since 2015. We will present a detailed workflow, a new software toolchain, guidelines and technical suggestions like the parametrization of the used EM-CCD camera.

30 In the application part of our manuscript, we will present a first test of the hypothesis of whether SR IR-RF allows deciphering single feldspar grains' bleaching history. We used a sample from the Médoc area (south-west France) previously dated using non-spatially resolved IR-RF for this test.

1.1 Spatially resolved luminescence dating

Conventional luminescence readers rely on photomultiplier tubes (PMT) to detect luminescence emissions (e.g., Bortolot, 35 2000; Bøtter-Jensen et al., 2000; Richter et al., 2015; Maraba and Bulur, 2017). However, equivalent dose (D_e) distributions deduced from multiple-grain aliquots tend to scatter more than individual analytical uncertainties can explain (for a brief overview on various reasons, see Fitzsimmons, 2019) and a PMT does not allow to distinguish simultaneously emitted signals from individual grains.

Single-grain systems, such as employed by Bøtter-Jensen et al. (2003), use a laser to optically stimulate luminescence (OSL, 40 Huntley et al., 1985) single grains sequentially. Hence, luminescence is collected grain wise. However, such a system does not suite when (1) the stimulation (heating, irradiation) can only be applied simultaneously to all grains, or (2) spatial mapping of the sample is desired (e.g., Duller and Roberts, 2018). For these reasons, luminescence imaging systems have been subject of research since, at least, the 1980s (cf. Huntley and Kirkley, 1985). In the 1990s, Charged Coupled Device (CCD) cameras became affordable and gained attraction for luminescence detection due to their high quantum efficiency in conjunction with

45 a relatively simple technical implementation into existing systems. A variety of experimental and commercial image systems based on CCD cameras were developed (Duller et al., 1997; Spooner, 2000; Greilich et al., 2002; Baril, 2004; Clark-Balzan and Schwenninger, 2012; Chauhan et al., 2014; Greilich et al., 2015; Kook et al., 2015; Duller et al., 2020). However, the number of publications making use of those systems in the context of actual dating appears to be surprisingly small (e.g., Greilich et al., 2005; Rhodius et al., 2015; Duller et al., 2015).

Deleted: 25

Deleted: 30 since 2015. We will present a detailed workflow and a new software toolchain and guidelines and technical suggestions like the parametrization of the used EM-CCD camera.¶

Deleted: 35

Deleted: 40

Deleted: (

Deleted:))

Deleted: ¶
45

Deleted: Charge

Deleted: ¶
50

50 Reasons for this lag of attention might be found in the technical complexity of luminescence imaging systems, combined with significant issues such as image noise or signal cross-talk (Gribenski et al., 2015; Cunningham and Clark-Balzan, 2017). Thus, luminescence imaging methods appear challenging to apply, and the efforts necessary to analyse the measurements might be considered disproportional to the scientific gain. To prevent spatially resolved IR-RF from failing for the same reasons, we intend to provide our software and methods as accessible, transparent and automated as possible.

55 1.2 The brief history of spatially resolved IR-RF dating

IR-RF dating applies ionising radiation to stimulate a fluorescence signal in K-feldspar at a wavelength of around 865nm (Trautmann et al., 1999). This IR-RF signal decays with the accumulation of dose and resets through optical bleaching (e.g., a few hours to days of sunlight exposure). Determining ages up to ca 600ka is reported in the literature (Wagner et al., 2010).

The early development of conventional non-spatially resolved IR-RF as dating technique was an effort of the group around 60 Matthias Krbetschek at the TU Freiberg (Germany) (Trautmann et al., 1998, 1999; Krbetschek et al., 2000; Erfurt and Krbetschek, 2003b). Their work cumulated in the infrared radiofluorescence single aliquot regenerative-dose (IRSAR) protocol (Erfurt and Krbetschek, 2003a). Although the IRSAR protocol is straightforward and promises extended temporal range, its invention had limited impact on the dating practice in Quaternary science (see Murari et al., 2021, for a detailed review).

One particular issue is the low bleachability of the IR-RF signal (at least two hours of natural sunlight, Trautmann et al., 65 1999), which potentially provokes partial bleaching effects. Other issues are potential inhomogeneities in the mineral composition and micro-dosimetry of the sample (Trautmann et al., 2000).

Seeking a technical solution, Krbetschek and Degering (2005)¹ conducted first spatially resolved (SR) IR-RF measurements on feldspars. In their experiment, the sample was irradiated from below with a ⁹⁰Sr/⁹⁰Y β-source. The RF signal was collected by a 45° mirror and a custom-made imaging optic, with the signal detected through an Electron Multiplying (EM)-CCD 70 camera. Images were analysed using the software *AgesGalore* (Greilich et al., 2006).

When M. Krbetschek joined the Freiberg Instruments GmbH, the capability to perform SR IR-RF measurements became part of the design of the commercial available *lexsyg research* reader (Richter et al., 2013). Contrary to the original design by Krbetschek and Degering (2005), in this system, the ⁹⁰Sr/⁹⁰Y source is placed above the sample position. A circular opening in the middle of the source module enables luminescence detection (Richter et al., 2012). A sketch of this *lexsyg research* RF 75 imaging module is shown in Fig. 1. With the early death of M. Krbetschek in 2012, the progression in the SR IR-RF technique's development came to a temporary hold.

2 Part I: Enabling spatially resolved radiofluorescence

¹ These results were never formally published. However, we are happy to share their presentation on the 11th International LED conference (2005, Cologne, Germany) upon request.

Deleted: methodological

Deleted: techniques

Deleted: ¶
55

Deleted: 60

Deleted: a

Deleted: 65

Deleted: submitted

Deleted: In the search for

Deleted: a

Deleted: mea-¶
70 surements

Deleted: ¶
75

Deleted:

Moved down [1]: Figure 1. (A) Technical sketch of the camera system for spatially resolved IR-RF measurements at the *lexsyg research* reader

Deleted: 'L2' in Bordeaux.

Moved down [2]: The collimating lens position and the camera's height were adjusted manually to obtain the best IR-RF image quality. (B) Typical image output of a natural IR-RF image stack. The upper picture shows an unprocessed but background-corrected SR IR-RF image taken with High SNR setting (see Table 2). Two speckle noise events caused by bremsstrahlung (white) and two grain IR-RF signals (yellow) are marked. Individual

Deleted: stainless-steel cup.¶

In the following section, we outline technical aspects of relevance for successful SR IR-RF measurements. Although we were bounded to tailor some settings to a particular system, the overall parametrisation and the developed workflow is fairly system independent. More detailed information is available in the Appendix and the referenced resources.

2.1 Equipment

All measurements presented in this manuscript were performed on a single Freiberg Instruments *lexsyg research* reader (Richter et al., 2013) at the IRAMAT-CRP2A in Bordeaux (reader name 'L2'). The system is equipped with a ring-shape type $^{90}\text{Sr}/^{90}\text{Y}$




Figure 1. (A) Technical sketch of the camera system for spatially resolved IR-RF measurements at the *lexsyg research* reader 'L2' in Bordeaux. The collimating lens position and the camera's height were adjusted manually to obtain the best IR-RF image quality. (B) Typical image output of a natural IR-RF image stack. The upper picture shows an unprocessed but background-corrected SR IR-RF image taken with High SNR setting (see Table 2). Two speckle noise events caused by bremsstrahlung (white) and two grain IR-RF signals (yellow) are marked. Individual grain signals are hardly distinguishable from the image noise. The lower image shows the processed image stack's median image, where light from individual grains is visible. The dashed white line marks the rim of the sample carrier (here a stainless-steel cup).

β -source (Richter et al., 2012) delivering ca 3.5Gymin^{-1} to K-feldspar grains with a size of $125\text{--}250\mu\text{m}$ (cf. Frouin et al., 2017).

For luminescence detection, we used a Princeton Instruments ProEM: 512B+ eXcelon EMCCD camera with a 512×512 pixel unichromatic back-illuminated CCD sensor. The camera sits on an automated detector changer, which allows also for spatially resolved TL and OSL measurements (cf. Richter et al., 2013; Greilich et al., 2015). The camera has a quantum efficiency (QE) of $> 80\%$ between 450nm and 750nm . At the K-feldspar IR-RF emission centred at ca 865nm the QE is

Deleted: 80

Deleted: ¶
85

Moved (insertion) [1]

Moved (insertion) [2]

Deleted: sitting

Deleted: .

Deleted: ¶
90

90 around 60%. For the IR-RF measurements, we placed a *Chroma D850/40x* interference filter between β -source and EMCCD camera. The custom-made optic has a numerical aperture (NA) of about 0.2 and a lateral magnification of 0.6, leading to an image resolution of 27 μ m per pixel. Prior to our experiments, we adjusted the optical focus by manually calibrating the camera's installation height until we obtained the best image quality in terms of sharpness and minimised distortion. [The nearby](#)

[⁹⁰Sr/⁹⁰Y \$\beta\$ -source shielding emits secondary X-ray photons \(bremsstrahlung, cf. Liritzis and Galloway, 1990\), which induce](#) 95 [localized high signal events at the CCD chip upon impact. The result are images speckled with bright spots \(see Fig. 1B\). We will refer to this effect as 'speckle noise'. It has to be noted that naturally occurring cosmic rays also cause similar bright spots. However, we approximated that cosmic rays are responsible for less than 1 % of the spots.](#)

[The system was equipped with a solar light simulator \(SLS\) system facilitating LEDs with broad peaks centred at 365nm, 462nm, 523nm, 590nm, 625nm and 850nm \(Richter et al., 2013\).](#) The system is the same as used for the experiments by 100 Frouin et al. (2015) and Frouin et al. (2017).

However, over the years, the system received a couple of hardware upgrades tackling various problems (cf. Kreutzer et al., 2017). In 2018, an improved drive train for the sample arm as well as modernised control hardware in conjunction with a new 100W at 48V Si₃N₄ heater controlled by a PT1000 thermocouple was installed (pers. communication Freiberg Instruments GmbH).

105 2.2 Software

Our software toolchain consisted of three different tools: *LexStudio2* for measurement sequence control, *ImageJ* for image processing and the R function library *Luminescence* for data analysis. *ImageJ* and the *Luminescence* package are open-source (GPL-3 licence) and freely available for all major platforms (*Windows, Linux, macOS*). However, our software toolchain was tested so far just on *Windows 10* and *macOS* (v10–v11). Detailed installation guides and additional download links to the SR 110 IR-RF specific software modules can be found at <https://luminescence.de>.

2.2.1 Image acquisition with *LexStudio2*

We used the software *LexStudio2* (version 2.5.0, 2019-11-01) shipped with the measurement system for sequence writing, camera parametrisation, and image acquisition. For the presented work, Freiberg Instruments updated *LexStudio2* in 2018/2019 with a new module to control the camera settings relevant for luminescence imaging (Fig. 2A). The new module also enables

115 sequence-synchronous camera control and data handling. Thus, sequence writing differs not from routine luminescence measurements with a PMT. The new *LexStudio2* camera module uses the 32-bit *PVCAM* drivers by Princeton Instruments and maintains the compatibility to the camera control software *WinView* shipped with the ProEM camera. Unfortunately, this [enhanced](#) version of *LexStudio2* is currently bound to 32-bit Microsoft Windows platforms. The obtained data, however, can

Moved (insertion) [3]

Moved (insertion) [4]

Moved (insertion) [5]

Moved (insertion) [6]

Moved (insertion) [7]

Moved up [6]: The system was equipped with a solar light simulator (SLS) system facilitating LEDs with broad peaks centred at 365nm,

Moved up [7]: 462nm, 523nm, 590nm, 625nm and 850nm (Richter et al.,

Deleted: ¶
100

Deleted: ¶
105

Deleted: <https://luminescence.de>.

Deleted: ¶
110

Deleted: en-¶
115 hanced

be separately processed and analysed on other computers with other platforms. The data consists of one image stack for each

¹²⁰ RF measurement, saved as a 16-bit greyscale TIF file. To prevent system crashes due to the 3 GB barrier of 32-bit platforms, *LexStudio2* provides an option to split large data sets automatically.

2.2.2 Image processing with *ImageJ*

For processing the image data, we used the open-source software *ImageJ* (version: 1.52p) (Schneider et al., 2012). We developed a macro called "SR-RF" (file SR-RF.ijm, see supplement) to automatise the workflow. The SR-RF macro is a plain

¹²⁵ ASCII-file and written in the JavaScript-like *ImageJ* macro language. It provides a graphical user interface (Fig. 2B) to simplify user-interactions. The output is an ASCII text file with the file-ending *.rf. The file contains the single-grain IR-RF curves, the size and spatial location of the associated regions of interests (ROIs) and further image processing information. We used the enhanced *ImageJ* distribution *Fiji* (<https://fiji.sc>) (version: 2.0.0-rc-69) for most of our analyses. A cross-platform version,




Figure 2. Screenshots of (A) the *LexStudio 2* interface to parametrise the CCD camera, and (B) the 'SR-RF' *ImageJ* macro interface to analyse IR-RF images.


of *ImageJ* and the SR-RF macro and all necessary plug-ins pre-installed can be downloaded from <https://luminescence.de>. A ¹³⁰ short description of how to install the SR-RF macro and its dependencies and detailed documentation of the macro can also be found on our website. Interfacing of the macro to other programs is possible through the additionally supported *ImageJ* batch-mode.

2.2.3 Data analysis with R

We employed the statistical programming environment R (R Core Team, 2020) and the package 'Luminescence' (Kreutzer ¹³⁵ et al., 2012, 2020) for processing the IR-RF single-grain data.

Deleted: 120

Deleted: 1



Moved down [8]: Figure 2.

Deleted: Screenshots of (A) the *LexStudio 2* interface to parametrise the CCD camera, and (B) the "SR-RF" *ImageJ* macro interface to analyse IR-RF images.

Moved (insertion) [9]

Deleted: We used

Moved (insertion) [8]

Deleted: 125

Deleted: enhanced

Deleted: distribution *Fiji* (<https://fiji.sc>) (version: 2.0.0-rc-69) for most of our analyses.

Moved up [9]: A cross-platform version

Deleted: <https://luminescence.de>.

Deleted: 130

Therefore, we developed two new functions for a seamless data import and processing of *.rf files:

Luminescence::read_RF2R() and Luminescence::plot_ROI() ('Luminescence' ≥ v0.9.8). Both functions work in conjunction with the already available function Luminescence::analyse_IRSAR.RF(). See below for an application example.

140 Advanced users can also deploy our experimental R package dedicated to spatially resolved luminescence data analysis called 'RLumSTARR' (Kreutzer and Mittelstrass, 2020a). The sole relevance of 'RLumSTARR' for this contribution is the function RLumSTARR::run_ImageJ(). We used this function to run *ImageJ* in a batch mode and auto process our image data. However, 'RLumSTARR' is not required to analyse SR IR-RF data.

2.3 Measurement protocol

145 We applied the RF₇₀ single aliquot protocol by Frouin et al. (2017), an improved version of the IRSAR protocol (Erfurt and Krbetschek, 2003a). The RF₇₀ sequence (Table 1) includes two IR-RF measurements: one for the natural signal (RF_{nat}) and one for the regenerated signal (RF_{reg}). In the data analysis process, the RF_{nat} signal curve is slid vertically and horizontally signal curve until to best match the RF_{reg} curve. The horizontal sliding distance is the accumulated dose needed to match the natural RF signal, thus defining the equivalent dose (Murari et al., 2018). Measurement durations are user-defined. However, 150 RF_{reg} should be longer than the sample's expected natural dose. RF_{nat} should not contain less than 70 data points (in our case images) to give sufficient statistical confidence when using the sliding method (Frouin et al., 2017, their supplement, proposed at least 40 channels for a resolution of 15 s/channel).

We used the comparable solar simulator settings as in Frouin et al. (2017)²: 365nm: 20mWcm⁻², 462nm: 61mWcm⁻², 525nm: 53mWcm⁻², 590nm: 37mWcm⁻², 623nm: 112mWcm⁻², 850nm: 94mWcm⁻². In our bleaching protocol,

155 the UV power settings are doubled in comparison to the recommendations by @frouin issue 2015. This setting may lead to an unwanted temperature increase in the sample. However, we carefully monitored the temperature as recorded by the thermocouple in the reader's sample arm. We found the temperature stable at 70°C for all measurements (data not shown), indicating that the temperature in the samples was stable.

Table 1. Applied IR-RF measurement sequence according to the RF₇₀ protocol by Frouin et al. (2017).

#	Step	Treatment	Measurement
1	Shallow trap depletion	Preheat at 70°C for 900s	-
2	Natural dose IR-RF	β -irradiation at 70°C for <user defined time>	RF_{nat}
3	Signal resetting	Bleaching with in-built solar simulator for 3h	-

² Contrary to what is quoted erroneously in Frouin et al. (2017), these settings are identical to the bleaching settings applied by Frouin et al. (2017) for their measurements.

Deleted: ¶
135

Deleted: A
Deleted: 140

Deleted: O

Deleted: 145

Deleted: 150
Deleted: same
Deleted: for the bleaching
Deleted: (2015) but with increased UV stimulation power:¶

4	Wait for phosphorescence to decay	Pause for 1h	-
5	Shallow trap depletion	Preheat at 70°C for 900s	-
6	Regenerative dose IR-RF	β -irradiation at 70°C for <user defined time>	RF_{reg}

2.4 Camera settings

[160](#) While the enhanced *LexStudio2* version automates image acquisition, it does not free the user from parametrising the camera. In the following, we will advise on the most relevant camera settings and their impact on image noise and signal sensitivity. We derive parts of our advice from signal-to-noise ratio (SNR) estimations summarised in Appendix A. Table 2 lists major correlations between CCD camera settings and data quality. Table 3 lists the camera settings we used in our experiments. For more in-depth insights into the scientific CCD camera technology we may refer to Janesick (2001) and the *Andor Learning Centre* (<https://andor.oxinst.com/learning/>; search for “Andor Academy”).

2.4.1 Set the CDD chip temperature low, but not too low

One primary source of image noise arises from the dark current of the CCD chip. The dark current is highly temperature dependent, [see Appendix A2 or Fig. S1 for the exact relation. The camera has an inbuilt thermoelectric cooling system to cool](#) the CCD chip [far below room](#) temperature and [thus effectively suppressing](#) dark current related image noise. [For the camera](#)

[170](#) we used, the lowest reachable CCD temperature is in theory at about -75°C if no additional external cooling is applied. For the [user](#), it seems obvious to set the target CCD temperature as low as the cooling system allows. However, we strongly recommend setting the target temperature between 10K and 15K above the [technical minimum](#). An RF measurement takes hours, enough time for the camera electronics to warm up, or change the system temperature. The resulting fluctuations in the

the CCD temperature induce changes in the background signal level during the RF measurement. These background instabilities [175](#) are hard to correct in the post-processing. Therefore, a stationary CCD temperature level is mandatory and eased by leaving the cooling system enough headroom for corrections.

2.4.2 Select a slow readout rate, but not too slow

[170](#) The CCD chip readout process induces another source of image noise called read noise or readout noise (cf. standard textbooks for both notations). Longer exposure times lead to better SNR because more signal is gathered while the readout noise remains [180](#) constant.

Another way to reduce readout noise is to choose a slow CCD readout rate. In our system, the slowest available readout rate is 100kHz. At this rate, a full resolution (512×512px) CCD readout takes 2.13s. If the readout process lasts longer than, [175](#) the RF measurement channel, either images are lost, or the camera runs asynchronous to the measurement sequence. In

Deleted: ¶
155

Deleted: (<https://andor.oxinst.com/learning/>;

Deleted: 160

Deleted: . Cooling

Deleted: by 10K quarters the dark current related signal background

Deleted: halves the

Deleted: (Fig. S1). Thus

Deleted: theoretical mini-¶
165 μm .

Deleted: 170

Deleted: ¶
175

our systems, the readout process started after the preset time interval for the image exposure ended. The camera is then locked until

185 the image data is transferred to the computer. Thus, the user has to incorporate a camera dead time when parametrising channel width and exposure time in the camera's sequence settings, see Table 3 and Appendix A. However, all modern scientific CCD cameras, including our *ProEM* camera, can read out the last image while already gathering signal light for the next image. The camera dead time is a setting particular to the *LexStudio2* software solution we used. Later software iterations or more advanced systems might set exposure time and channel width equal by default.

190 2.4.3 Do not use EM gain

EM-CCD cameras have an electron-multiplying (EM) register that amplifies the detected signals above readout noise if activated. The EM-mode allows for highly sensitive high-frame-rate imaging, but it comes at costs. (1) It induces an additional source of image noise (excess noise), (2) it reduces the dynamic range and the linearity of the signal acquisition, (3) it amplifies dark current signals and thus dark noise, and (4) it amplifies local pixel over-exposures leading to pixel-well overflows.

195 Especially the last point is problematic for RF imaging. If the speckle noise caused by bremsstrahlung gets amplified by the EM-mode, streaks with increased signal values appear on the image. These are hard to remove by image processing algorithms.

2.4.4 Consider hardware pixel binning

The most straightforward approach to improving the SNR and the signal sensitivity is pixel binning performed by the CCD camera image processing software like *ImageJ*. This software pixel binning, however, is less effective than potential hardware 200 binning by the camera. With applied hardware pixel binning, multiple pixels are considered as one pixel and read out together. This feature reduces the readout noise per imaged area and reduces the readout time and therefore the camera dead time (if applicable). As a side effect, the image stacks' file size is also reduced, positively impacting image processing time. We applied 2x2 pixel binning as a default setting and deactivated it only if we had sufficiently bright samples. On the downside, pixel binning lowers the camera resolution to 256x256 pixel, corresponding to a decreased spatial resolution of 54µm (before

205 27µm).

Table 2. Correlation between basic camera settings and data quality. Up arrows: Increasing this parameter leads to an increase of, e.g., noise, time span, intensity. Down arrow: Increasing this parameter leads to a decrease of the corresponding attribute. Right arrow: Changed parameter settings do not affect the attribute.

Camera setting	Source of information loss	Data quality
Readout noise	Dark noise	Dead time
per ROI and image	per ROI and image	per image*
		Signal per pixel
		SNR

Deleted: ¶
180

Deleted: ¶
185 (exceed

Moved up [3]: ⁹⁰Sr/⁹⁰Y β-source shielding emits secondary X-ray photons (bremsstrahlung, cf. Liritzis and

Moved up [4]: Liritzis and Galloway, 1990), which induce localized high signal events at

Moved up [5]: images speckled with bright spots (see Fig. 1B). If this

Deleted: The nearby

Deleted: localized high signal events at

Deleted: CCD chip upon impact. The result is

Deleted: If this

Deleted: -

Deleted: it causes

Deleted: 190 which

Deleted: ¶
195

Moved down [10]: Dark noise

Moved (insertion) [10]

Inserted Cells

Deleted: -SNR

Inserted Cells

Moved down [11]: per ROI and Image

Moved (insertion) [11]

Exposure time	⇒	↑	⇒	↓	↑
Readout rate	↑	⇒	↓	⇒	↓
Pixel binning	↓	⇒	↓	↑	↑
CCD temperature	⇒	↑	⇒	⇒	↓

camera dead time occurs only if a sequential CCD chip readout mode is applied (Full Frame mode)

Deleted: -↑→

Deleted: →⇒↓

Deleted: -↑→

Deleted: →⇒↑→⇒⇒↓

Table 3. Recommended settings for a Princeton Instruments *ProEM512* camera employed in a Freiberg Instruments *lexsyg research* system.

Camera setting	High SNR (default)	Full resolution
Channel width	5s	5s
Exposure time	4.15s	4.5s
Readout rate	100kHz	1MHz
Pixel binning	2 x 2	off (1 x 1)




Figure 3. Image processing workflow as performed by the *ImageJ* macro *SR-RF.ijm*. Note: The grey step 2 images show the signal value differences between the median signal values of the natural dose RF images and the median signal values of the regenerated dose RF images.

A homogeneous color means that the images are aligned.

2.5 Image processing

We obtain two *.tif files respectively image stacks (a series of images per file) per aliquot from the RF_{70} protocol (Table 1). Both image stacks are affected by speckle noise. Besides, the RF_{reg} images might be displaced or rotated compared to the RF_{nat} images due to uncertainties in the aliquot positioning (Kreutzer et al., 2017).

Both issues and the grain identification, are addressed by the SR-RF macro in *ImageJ*. The image processing has four steps (Fig. 3): (1) Speckle noise is removed, (2) both image stacks are geometrically aligned, (3) individual grains are identified, and (4) single grain RF curves are extracted. Table 4 gives recommendations for the macro settings. For more details on the macro

Moved (insertion) [12]

Deleted: 200

Deleted: caused by bremsstrahlung.

Deleted: 205

Deleted: ¶

Moved up [12]: Figure 3. Image processing workflow as performed by the *ImageJ* macro *SR-RF.ijm*.

Deleted: deployed

[settings and the detailed sequence of ImageJ commands](#), we refer to our SR-RF macro documentation [available at https://luminescence.de](#).

Deleted: on https://luminescence.de as well as the *ImageJ user guide* by Ferreira and Rasband (2012).

215 2.5.1 Step 1: Median filter

We used the *ImageJ* command *Grouped Z Project* (Ferreira and Rasband, 2012) to erase bremsstrahlung's spots. The images of both image stacks are grouped in quantities according to the user-defined parameter *Group Size*. Each group's images are combined to one image by taking the median pixel value for each pixel location. This process removes signal outliers while maintaining the fundamental shape of the signal curve (Velleman, 1980). Speckles caused by bremsstrahlung

Deleted: 210

220 occur in random locations. Hence, it is unlikely that the same pixel is affected more than once during a time interval related to the measurement of just a few images. The statistical likelihood of surviving speckles increases with longer image exposure times but decreases with larger group sizes. For the measurement system we used, and with an exposure time of 5s, a group size of five is sufficient to eradicate speckle noise.

Deleted: 215

2.5.2 Step 2: Image alignment

225 We used the *ImageJ* plug-in *TurboReg* by Thévenaz et al. (1998) to detect and correct aliquot movement. It is the same algorithm used by Greilich et al. (2015). The RF_{nat} and the RF_{reg} stack are aligned by comparing their global median images. Equal to other regression algorithms, the differences between median images are summed up to one residual value. The RF_{reg} median image is rotated and translated until the minimum is found. The rotation and translation parameters are then applied to all images of the RF_{reg} stack.

Deleted: ¶
220

230 To interpolate the signals for the fine movement of the alignment, *ImageJ* offers three methods none, bilinear and bicubic (Ferreira and Rasband, 2012). We tested the interpolation methods for sample TH0 (see below, Sec.3.4.1) and selected bicubic as hidden preset value.

Deleted: a

Deleted: ¶
225

Deleted: .

2.5.3 Step 3: Grain detection and ROI assignment

We used the *ImageJ* command *Find Maxima* (Ferreira and Rasband, 2012) to identify individual mineral grains. As [reference](#) image serves the arithmetic mean image of the two median images from step 2 (Sec.2.5.2). There, the *Find maxima* algorithm searches for local maxima in the pixel values. The user-defined parameter *Noise tolerance* controls the algorithm's sensitivity, which defines how much higher than the surrounding area a pixel value must be. A higher *Noise tolerance* value leads to higher robustness against optical reflections and signal outliers but a lower grain detection likelihood. A circular ROI is assigned to each local maximum. The diameter of these circles is user-defined through the [ROI](#)

Deleted: reference

Deleted: ¶
230

240 [diameter parameter](#).

Deleted: diameter parameter.

Deleted: 235

2.5.4 Step 4: Extract single RF curves

We used the *ImageJ ROI manager* to obtain the arithmetic mean of the pixel values in each ROI for each image in the RF_{nat} stack and RF_{reg} stack. Thus, the consecutive average signal in one ROI forms the IR-RF curve of one sample grain. These single grain IR-RF measurements and the lateral position of each ROI, are saved into one ASCII text file (table.rf) to be [245](#) further analysed with other software than *ImageJ*.

Table 4. Recommended SR-RF macro settings for the first image processing run, depending on the sample brightness and the grain size. Parameter refinements depending on the system and the sample might be necessary. The two lower columns display the properties of the resulting single-grain IR-RF curves. The sample area diameter values assume a lateral magnification of 0.6 and a pixel size of 16 μ m.

Macro parameter	~50–80 μ m grain size		~180–250 μ m grain size	
	Bright sample at	Dim sample at	Bright sample at	Dim sample at
	full resolution*	high SNR setting*	full resolution*	high SNR setting*
Image group size	5	5	5	5
Noise tolerance	15	10	15	10
ROI diameter	5	3	12	7
Time resolution of single-grain IR-RF curve	25s	25s	25s	25s
Diameter of sample area covered by ROI	133 μ m	160 μ m	324 μ m	371 μ m

*refers to the recommended camera settings in Table 3.

2.6 Single grain data analysis in R

We analysed the single grain IR-RF data the same way that we would analyse conventional PMT IR-RF measurements. A simple R script to analyse the table.rf file of one aliquot reads as follows (R package 'Luminescence'):

Moved (insertion) [13]

Deleted: 240

Moved (insertion) [14]

Moved (insertion) [15]

Moved (insertion) [16]

Deleted: `#load R package 'Luminescence'
library(Luminescence)`

```
#load R package 'Luminescence' library(Luminescence)
```

```
#import data file <-
```

```
file.choose()
```

```
RF_data <- read_RF2R(file)
```

```
#get ROI locations (optional)
```

```
ROI_data <- plot_ROI(RF_data)
```

```
#determine equivalent doses equivalent_doses <-  
analyse_IRSAR.RF(object = RF_data, method =  
"SLIDE", method.control = list(vslide_range = "auto",  
correct_onset = FALSE))
```




Figure 4. IR-RF cross-talk profile of one single grain. The inset shows the *ImageJ* image with the rectangle area selected for the profiling over ca 1,800 Gy (along the all image slices of the image stack). The solid black lines show the IR-RF signal. For illustrative reasons, we show only a few curves. The dashed blue line shows the approximated OSL cross-talk profile recorded by Gribenski et al. (2015) after a dose of ca 100 Gy. The violet shaded area approximates the grain (not in height but width). Please note that the data by Gribenski et al. (2015) were only added to provide a rough qualitative comparison. Please note that the metric distances (sub-labels) refer to the chip surface.

Moved up [13]: Table 4.

Moved down [17]: Here, the new function `read_RF2R()` converts the `table.rf` file into a list of `RLum.Analysis` objects. Each `RLum.Analysis`

Moved down [18]: Each `RLum.Analysis`

Deleted: Recommended SR-RF macro settings for the first try, depending on the sample brightness and the grain size.

Moved up [14]: Parameter refinements depending on the system and the sample might be necessary.

Moved up [15]: ¶
Macro parameter

Deleted: ¶
Bright sample at Dim sample at ... [1]

Moved up [16]: 'refers to the recommended camera settings in Table 3.¶

Deleted: object contains the RF_{nat} and RF_{reg} curves of one ROI. The equivalent dose of each ROI is calculated by `analyse_IRSAR.RF()`¶ ... [3]

Moved down [19]: (2017). The resulting dose distribution can be displayed and further evaluated by any of the various functions for dose statistics, the 'Luminescence'

Moved down [20]: Vertical sliding can improve the equivalent dose results' accuracy but need a significant curvature in the IR-RF decay to work ¶

Deleted: `#import data file <- file.choose()` `RF_data <- read_RF2R(file)`¶
`#get ROI locations (optional)`¶ ... [2]

Deleted:

Deleted: red

Deleted: blue

[#plot_dose_distribution_plot](#) `AbanicoPlot(equivalent_doses)`

Here, the new function `read_RF2R()` converts the `table.rf` file into a list of `RLum.Analysis` objects. Each `RLum.Analysis` object contains the RF_{nat} and RF_{reg} curves of one ROI. The equivalent dose of each ROI is calculated by `analyse_IRSAR.RF()` which was already introduced and used by Frouin et al. (2017). The resulting dose distribution can be displayed and further evaluated by any of the various functions for dose statistics, the 'Luminescence' package provides. In the example above, we allowed vertical sliding after Murari et al. (2018) in the function `analyse_IRSAR.RF()` (parameter `vslide_range`).

Vertical sliding can improve the equivalent dose results' accuracy but need a significant curvature in the IR-RF decay to work properly. Vertical sliding can be deactivated by setting `vslide_range = NULL` or removing the parameter. The function `plot_ROI()` displays and returns the ROI locations and returns the euclidean distance between them. This information is useful to study the impact of signal cross-talk.

2.7 Signal cross-talk

An issue in OSL and TL imaging flagged by Gribenski et al. (2015) and further discussed by Cunningham and Clark-Balzan (2017) is signal cross-talk. Two independent effects cause signal cross-talk: (1) signal light misdirected by optical aberrations and (2) signal light backscattered by the silicone fixation layers and the sample carrier's surface. The visual perceptions are blurry luminescence images and signal halos around individual grains. These halos can extend into the ROIs of near located other grains. This cross-talk effect blends the IR-RF curves and potentially narrows the D_e distribution.

Gribenski et al. (2015) investigated the effects of signal-cross talk in spatially resolved OSL measurements. They found a substantial effect on the equivalent dose outcome and supposed optical aberrations as the primary signal cross-talk source. Like us, they used a *lexsyg research* device equipped with a *ProEM512B* camera. However, they measured at the OSL/TL sample position equipped with a custom-made multi-purpose optic (Richter et al., 2013; Greilich et al., 2015). The OSL/TL optic was designed with large opening angles and high UV-to-NIR transmittance. This design decision enabled a maximum of signal yield for various applications but counteracted the optical correction of spherical and chromatic aberration and their secondary effects like astigmatism.

The optic of the RF position has a far smaller aperture ($NA_{RF} \approx 0.2$ vs $NA_{OSL/TL} \approx 0.5$) and therefore less spherical aberration. In addition, we consider chromatic aberration as negligible because we performed the focus calibration and all measurements at the same wavelength (865nm). As Fig. 4 shows, the effect of signal cross-talk appears to be weaker in our measurements as observed by Gribenski et al. (2015) and should be insignificant for inter-grain distances above ca 500 μ m. We tried to maintain this distance by preparing our samples with a very low grain density.

Nevertheless, for samples with a high grain density or a high grain intensity inhomogeneity, signal cross-talk will be an issue. We propose the following countermeasures to reduce the effect; none of them applied in our experiments though:

- Special sample carriers: punched or black or polished to minimize backscattered luminescence light

Moved (insertion) [17]

Moved (insertion) [18]

Moved (insertion) [19]

Moved (insertion) [20]

Deleted: 250

Deleted: 255

Deleted: ¶
260

Deleted: 265

Deleted: 270

– Improved optics: A more specialized optic (the lenses are exchangeable) can further reduce spherical aberration

280 – Application of mathematical corrections, such as suggested by Cunningham and Clark-Balzan (2017)

3 Part II: Testing spatially resolved radiofluorescence

3.1 Samples

We selected two potassium bearing (K-feldspar) samples to apply and test our SR IR-RF tools and their settings. The first sample (TH0, grain size: 125–250 μm) is a modern analogue sample of aeolian origin from the Sebkhah Tah in Morocco (cf. 285 Bouab, 2005). It is the same sample used by Frouin et al. (2017) to calibrate the $^{90}\text{Sr}/^{90}\text{Y}$ source of the very same reader used, for our measurements here. The sample was exposed to a γ -dose of 56.02Gy ($c_v \sim 2\%$) in 2015 (Frouin et al., 2017). The second K-feldspar sample (BDX16651, grain size: 100–200 μm) originates from a coastal dune in the Mécoc area (south-west France). For this sample, Kreutzer et al. (2018) estimated a palaeodose of 50.7 \pm 5.7Gy for the quartz fraction (green OSL) and 96.2 \pm 8.0Gy (with IR-RF) for the here measured K-feldspar fraction. For details on the sample preparation procedures, 290 we refer to the cited literature.

3.2 Experiments

TH0 allowed us to calibrate the $^{90}\text{Sr}/^{90}\text{Y}$ source with SR IR-RF and compare the results with the PMT's calibration measurements. For this experiment, the detector changed in alternating turns, i.e. after measuring an aliquot with the PMT, another aliquot was measured using the EM-CCD camera, and then we measured an aliquot again with the PMT, and so on. We tested 295 whether both measurements estimate statistically indistinguishable source dose rates.

The measurements of BDX16651 aimed at one main application of single grain measurements: differentiation between grain fractions with different bleaching history. Kreutzer et al. (2018) reported an age of 37.0 \pm 4.9ka (arithmetic average \pm standard deviation) for the feldspar fraction (measured with IR-RF) and 26.1 \pm 3.5ka for the quartz fraction (measured with green OSL). While both ages overlap within 2σ , Kreutzer et al. (2018) reported consistently older ages for the feldspar fraction 300 compared to the quartz fraction for all samples from the site. Therefore, they argued that the natural bleaching was likely insufficient to reset the IR-RF signal of the feldspar grains. SR IR-RF should confirm the quartz result obtained by Kreutzer et al. (2018) and potentially enable us to identify those grains that received a full signal resetting before the last burial.

For both samples, feldspar grains were dispersed randomly on stainless-steel cups aiming at a low grain density. The sample cups were sprayed with a thin layer of silicon oil. However, no mask or other aid was used because this reflects are

305 realistic aliquot preparation procedure in most laboratories. We aimed at 30 to 50 grains per aliquot. We prepared at least three cups per sample. Irradiation times were equal to values reported in Frouin et al. (2017) and Kreutzer et al. (2018): 3,600s (RF_{nat}) and 30,000s (RF_{reg}) for sample TH0; 3,600s and 10,000s for sample BDX16651.

Deleted: 275

Deleted: 280

Deleted: southwest

Deleted: 285


Deleted: 290

Moved (insertion) [21]

Deleted: for the feldspar fraction and

Deleted: 26.1 \pm 3.5ka for the quartz fraction.

Moved up [21]: While both ages overlap within 2σ , Kreutzer et al. (2018) reported consistently older



Moved down [22]: Figure 5. Typical IR-RF curves for the sample TH0 (left) and BDX16651 (right). Both curves were extracted from ROIs following the procedure outlined in the first part of the manuscript. For determining the D_e the sliding method was used. Due to the absence of any curvature in the observed dose range, no vertical sliding was applied to sample BDX16651 measurements (B).

Deleted: SR-RF macro settings as follows: image group size: 5, noise tolerance: 20 (TH0), 30 (BDX16651), grain diameter: 7. Deleted: ages for the feldspar fraction

Deleted: 295

Deleted: 300

Figure 5 shows typical IR-RF curves from one ROI (in our case one grain) for TH0 (Fig.5A) and BDX16651 (Fig.5B).

To obtain the D_{es} , we applied the vertical and horizontal sliding technique (Murari et al., 2018) to TH0. [The vertical sliding 310 ensures that both curves \(\$RF_{nat}\$ and \$RF_{reg}\$ \) match best based on their shape. This approach was first used by Kreutzer et al. \(2017\) to corrected for changed signal intensities due to geometry issues. Still, it can also be used to correct sensitivity changes \(Murari et al., 2018\). For sample BDX16651, only horizontal sliding was used due to the absence of visible curvature in the IR-RF curve.](#)

As rejection criteria, we applied the default test criteria (cf. Froin et al., 2017, their supplement) of the function `analyse_IRSAR.RF()`. Two of those criteria were of relevance for our contribution: `curves_ratio` and `curves_bounds`. The first calculates the ratio of RF_{nat} over RF_{reg} in the range of RF_{nat} . If it exceeds a certain threshold (here 1.001) it usually indicates that the RF_{nat} best matched the RF_{nat} while lying above the RF_{reg} (additionally confirmed by visual inspection), violating the assumption that the highest IR-RF signal is observed for the RF_{reg} after bleaching. If the second, `curves_bounds`, criterion is flagged, the RF_{nat} cannot match the RF_{reg} within the measured range of RF_{reg} ; [an observation](#) usually made for very noisy, flat curves.

The raw data of our measurements, along with the applied R scripts and partially pre-processed are available open-access (Kreutzer and Mittelstrass, 2020b).




Figure 5. Typical IR-RF curves for the sample TH0 (left) and BDX16651 (right). Both curves were extracted from ROIs following the procedure outlined in the first part of the manuscript. For determining the D_{es} the sliding method was used. Due to the absence of any curvature in the observed dose range, no vertical sliding was applied to sample BDX16651 measurements (B). Please note, for sample BDX16651 only the first 8,000 s of the RF_{reg} are displayed in the figure due to a technical error. SR-RF macro settings as follows: image group size: 5, noise tolerance: 20 (TH0), 30 (BDX16651), grain diameter: 7 px.

3.3 Technical camera issues

Deleted: and used only horizontal sliding for sample BDX16651 due to the absence of visible curvature in the IR-RF curve...

Deleted: 305

Deleted: 310

Deleted: observation

Moved (insertion) [22]

While we measured at least three cups with grains per sample, the number of usable cups presentable here finally narrowed down to one cup each. A malfunction in the cooling system of our camera stopped us from conducting more measurements.


This cooling system degraded over the last five years, continually increasing the lowest reachable temperature from at least -70°C in 2015 to about -45°C in 2019. As we already mentioned above, the CCD chip temperature's spatial and temporal uniformity is necessary to ensure a stable and homogeneous signal background. We provide additional insights AppendixA2 and Figs. S1 and S2 in the supplement. Unfortunately, our camera's cooling system finally lost its ability to maintain stable chip

temperatures during our measurements meant for publication. Significant variations in the IR-RF curves' signal background required us to discard most of our measurements (see Fig. S4 for an example).

Independently from this issue, we further discarded grains located at the rim of the stainless-steel cup, where our analysis indicated exceeded IR-RF curve boundaries for unknown reasons (i.e. no match between RF_{nat} and RF_{reg}).

3.4 Results

Figure 6 illustrates the final results for the two remaining cups. One for TH0 (Fig.6A, upper part) and one for BDX16651 (Fig.6B, lower part). For each sample, we show an image taken with the camera (left-hand side) during the measurements and an Abanico plot (Dietze et al., 2016) of the distribution of the results. ROI pixels (diameter 7px, see Table 4) taken for the D_e analysis are coloured green and numbered. The numbers are displayed again in the Abanico plots (right-hand side). The results



Deleted: 315

Deleted: ¶
320

Deleted: 325

Deleted: 330

Moved down [23]: of TH0 display dose rates in Gys⁻¹ and equivalent doses in Gy for BDX16651.

Deleted: We applied the average dose model (Guérin et al., 2017) to both distributions with an assumed σ_m of 0.05.¶

Moved down [24]: -3.4.1-TH0¶
SR RF-RF measurements of sample TH0 on 10 grains (ca 20 grains on the cup, 11 grains emitted sufficient light for the analysis, one grain discarded) obtained a source-dose rate of $0.055 \pm 0.004\text{Gys}^{-1}$ (date: 2019-09-13).

Deleted: This value is consistent with the¶
335 source-dose rate calibration value obtained through conventional IR-RF PMT measurements with the same sample (Fig. S5,

Moved down [25]: measurement date: 2019-09-13, n = 10, $0.056 \pm 0.001\text{Gys}^{-1}$). Hence, it confirms our hypothesis that the calibration results obtained through SR IR-RF and IR-RF PMT measurements are indistinguishable. Furthermore, it gives some confidence that these measurements were not affected by the cooling-system malfunction for the camera.¶
We further tried to determine to which extent the results depend on chosen ROI size (here diameter 7px) and the interpolation

Deleted: ¶
340 method used to correct the image for translation and rotation (Sec.2.5.2).

Moved down [26]: As interpolation method, we obtained best results for

Deleted: the option bicubic (see Fig.

Moved down [27]: S3) which is the default in the SR-RF *ImageJ* macro SR-RF. The ROI diameter should mimic the approximated grain size or be a bit larger (see also Fig. S3). We observed a plateau of results for ROI sizes between 5px ¶

Deleted: ¶
<object><object>TH0 (camera)¶




Figure 6. The figure shows the SR IR-RF measurement results for single grains from samples TH0 (A, top) and BDX16651 (B, bottom). For each sample, the image of one aliquot with the selected ROIs (green) is plotted on the lefthand side, and the resulting D_e distribution as Abanico plot (Dietze et al., 2016) on the righthand side. Numbers (white) in the plots identify individual ROIs. The distribution for TH0 shows dose rates and the distribution for BDX16651 equivalent doses. Note: The [original](#) images returned by the SR-RF macro [have been cropped and reworked in R for this publication](#).


[of TH0 display dose rates in Gys⁻¹ and equivalent doses in Gy for BDX16651. We applied the average dose model \(Guérin 340 et al., 2017\) to both distributions with an assumed intrinsic overdispersion \(\$\sigma_m\$ \) of 0.05.](#)

3.4.1 TH0

Deleted: SR-RF macro returns ROI images only as low-res *.png files. Thus for illustrative reasons, the ROI overlay images were produced manually for this manuscript from...

Deleted: 'SR-RF Image'

Moved down [28]: BDX16651 (camera) – FMM ¶



Deleted:

Moved (insertion) [23]

Moved (insertion) [24]

SR RF-RF measurements of sample TH0 on 10 grains (ca 20 grains on the cup, 11 grains emitted sufficient light for the analysis, one grain discarded) obtained a source-dose rate of $0.055 \pm 0.004 \text{Gys}^{-1}$ (date: 2019-09-13). This value is consistent with the source-dose rate calibration value obtained through conventional IR-RF PMT measurements with the same sample (Fig. S5, measurement date: 2019-09-13, $n = 10$, $0.056 \pm 0.001 \text{Gys}^{-1}$). Hence, it confirms our hypothesis that the calibration results obtained through SR IR-RF and IR-RF PMT measurements are indistinguishable. Furthermore, it gives some confidence that these measurements were not affected by the cooling-system malfunction for the camera.

We further tried to determine to which extent the results depend on chosen ROI size (here diameter 7px) and the interpolation method used to correct the image for translation and rotation (Sec.2.5.2). As interpolation method, we obtained best results for the option bicubic (see Fig. S3) which is the default in the SR-RF *ImageJ* macro SR-RF. The ROI diameter should mimic the approximated grain size or be a bit larger (see also Fig. S3). We observed a plateau of results for ROI sizes between 5px and 10px for sample TH0. Smaller values should not be selected because the ROI finding algorithm may not reliably select the grain centre. For larger values, signal cross-talk effects likely become an issue. Although the median appears to be rather robust for all ROI sizes between 5px and 30px for bicubic (Fig. S3).

355 3.4.2 BDX16651

We counted ca 40 grains on the analysed cup and 35 emitted light and were analysed. We discarded three grains because the R analysis indicated a bad match of RF_{nat} and RF_{reg} . The sample shows a large D_e scatter with an average D_e of $148.6 \pm 6.7 \text{Gy}$ (average dose and associated standard error (SE)). This value is significantly larger than the mean D_e of ca 96Gy reported by Kreutzer et al. (2018). However, in contrast to the study by Kreutzer et al. (2018), the single grain data allow further statistical treatment of the results. We applied the Finite Mixture Model (FMM, cf. Galbraith and Roberts, 2012) using the function Luminescence::calc_FiniteMixture() with an assumed sigmab value of 0.05 (Fig. 7). The Bayesian information criterion indicated the statistically significant number of components.

We found that four-dose components can best describe the D_e distribution. The lowest ca 81Gy (blue colour, Fig. 7) contains only 10% of all grains, the 2nd component ca 26%, the 3rd ca 47% and the highest dose component ca 19% of all grains. The

number varies with sigmab (not shown), but the dataset seems to consist of at least two dose groups (around < 120Gy and > 120Gy). Assuming that the lowest dose group (Fig. 7) corresponds to the best bleached grains (leaving aside possible layer disturbance and dose rate heterogeneities) the D_e of $81.3 \pm 3.4 \text{Gy}$ corresponds to an IR-RF age of ca $31 \pm 5 \text{ka}$, this is more consistent with the quartz age of $26.1 \pm 3.5 \text{ka}$. However, the overall statistical confidence in ages based on three grains might be doubted, regardless the statistically justified number of components. Simultaneously, it appears that dose groups with higher

Moved (insertion) [25]

Moved (insertion) [26]

Moved (insertion) [27]

Moved down [29]: Standard error
 $5 \rightarrow 2.5 \rightarrow 1.7$

Deleted:

Moved down [30]: $-0.0 \rightarrow 0.2 \rightarrow 0.4 \rightarrow 0.6 \rightarrow 0.01$
Precision = Density (bw 16.723)
Figure 7. Abanico plot for sample BDX16651 with coloured polygons indicating dose components as identified by the finite mixture model.

Moved down [31]: Further details see maintext.

Deleted: 345

Deleted: 350


Deleted: 355

Deleted: 5Gy

Deleted: 5Gy

Deleted: 360

370 doses than reported by Kreutzer et al. (2018) are dominant. Here more measurements would be needed to infer a statistically robust answer.



Moved (insertion) [28]

Moved (insertion) [29]

Moved (insertion) [30]

Figure 7. Abanico plot for sample BDX16651 with coloured polygons indicating dose components as identified by the finite mixture model. Further details see maintext.

Moved (insertion) [31]

4 Discussion

We showed that SR-RF is technically feasible and presented first results. However, some aspects deserve critical consideration.

4.1 The technical dimension

375 It would be wishful thinking to assume that the work is finished. In comparison to PMT measurements, the number of control parameters exploded similar to the amount of data. We tried to reduce the complexity by recommending meaningful settings and limit the number of adjustable parameters to a minimum. Still, other systems might have options we did not consider in our contribution.

380 Besides the technical problem we encountered with the detection chip's cooling system, we also acknowledge that our system is not perfect. A considerable improvement of image quality can be expected from a dedicated RF imaging system. We outline a possible design for such a system in Fig. 8. A system of one or two concave mirrors would allow to relocate the camera and the filters further away from the β -source and thus minimise bremsstrahlung effects and potential filter degradation (cf. Gusarov et al., 2005). Such a mirror optic would also eliminate chromatic aberration and thus enable the

Deleted: 365

Deleted: 370

Deleted: A focusing off-axis parabolic mirror

Deleted: .

Deleted: reduce spherical aberration given that a large mirror is chosen

ability to take RF images at different wavelengths without refocusing. A dedicated RF optic would also address further optical aberrations and

thus reduce signal cross-talk. As a camera, we propose a modern scientific CMOS camera. CMOS cameras have lower readout noise than traditional CCD cameras although they do not support EM and hardware pixel binning.




Figure 8. Instrumental design proposal for a dedicated SR-RF reader based on a Freiberg Instruments *lexsyg research*.

Concerning the software, one subject for future improvements we did not implement is an advanced median filter in the image processing macro. While the current algorithm proved itself powerful in sufficiently removing speckle noise, it decreases the time resolution and deletes those pixel values which are not identified as median values. More sophisticated algorithms

deploy complex running median processes. For example, the (53H, twice)-algorithm described in Velleman (1980) would mostly maintain time resolution while being still as potent in removing spikes. Another example: A (4253H, twice)-algorithm Velleman (1980) would maintain the shape of the underlying RF curve while smoothing away signal spikes and much of the Gaussian noise.

Another subject of potential improvements is the ROI assignment algorithm. The current algorithm assigns the maximum signal pixel of the grain as the centre of the ROI, no matter if this is the middle of the grain. We suggest a subsequent algorithm which refines the ROI centre towards an estimated grain centre. Consequently, the ROI size could be reduced without losing signal, usually leading to higher inter-aliquot scatter. This would increase the grain separation and decrease any influence of signal cross-talk.

Finally, while the presented software toolchain is open-source, hence freely available and open to inspections and improve-

Deleted: 375 (spherical aberration decreases with lenses/mirrors of larger diameter). Signal cross-talk might not be eliminated but probably significantly reduced....

Moved (insertion) [32]

Deleted: ¶
380

Deleted: 385

Deleted:

Moved up [32]: Figure 8. Instrumental design proposal for a dedicated SR-RF reader based on a Freiberg Instruments *lexsyg research*.¶

Deleted: 390

Deleted: improvements

[400 ments](#), we acknowledge that the combination of three different software tools adds an additional layer of complexity. Although, in particular, the image processing through *ImageJ* has the advantage that the data processing is transparent and available on all platforms and independent of the particular measurement system. Furthermore, users can tap into an extensive repository of available functions and plug-ins to record their own macros and thus adjust the image analysis with *ImageJ* without a need for programming skills.

Deleted: 395

[405](#) 4.2 The [application](#) dimension

Deleted: scientific

This section alludes to the scientific gain and the initially expressed hypothesis that SR IR-RF can unravel the bleaching history of single feldspar grains.

We showed for sample TH0 that obtained source dose-rate results do not differ significantly from conventional IR-RF results using a PMT. This observation is reassuring because it shows that the presented workflow and analysis leads to meaningful

Deleted: ¶
400

[410](#) results. However, Fig.6A also reveals a large scatter between the individual feldspar grains ranging from 0.044Gys^{-1} to 0.076Gys^{-1} . Richter et al. (2012) reported a variation of the radiation field for our source type of only 2%. Hence, the extreme values might result from microdosimetric effects (irradiation, cf. Mauz et al., 2020), are related to IR-RF characteristics of single feldspar grains [or varying K-concentrations \(e.g., Dütsch and Krbetschek, 1997\)](#).

Deleted:) or

Deleted: .

Kumar et al. (2020) reported zoning of feldspar grains linked to the geochemical composition. On some [of our images \(not \[415\]\(#\) shown\)](#), it appears that the light is not evenly distributed over the grain surface. However, higher optical resolutions would be required to investigate this aspect further.

Deleted: 405 of our images (not

Sample BDX16651 showed an even higher scatter in the equivalent doses, which is not surprising for a natural sediment sample. While [environmental](#) dose rate heterogeneities might add to the observed scatter (Fig.6B), the internal K concentration of K-feldspar (cf. Huntley and Baril, 1997), in our case contributing ca 23% to the environmental dose rate (cf. Kreutzer,

Deleted:)

Deleted: et al., 2018) weakens [410](#) the effect.

[420 et al., 2018](#)). [weakens the effect. Grain-to-grain variations in the internal K-concentrations would undoubtedly broaden the \$D_e\$ distribution. However, in our case, the K-concentration was sufficiently constrained by energy dispersive X-ray analysis \(EDX\) \(Kreutzer et al., 2018, their Fig. S16\) at \$11.4 \pm 2.5\%\$ ³. This value does not have enough leverage to cause results, such as observed for our sample. More important is to keep in mind that IR-RF specifically targets K-feldspar grains, which is amplified by selecting single grains with the highest luminescence intensities and presumed relatively homogeneous K-\[425 concentrations\]\(#\)](#). Hence, it is more likely that the distribution reflects different bleaching histories with a lower D_e component (Fig.7) that gives a luminescence more consistently than the quartz age.

The small number of overall observations, however, does not yet support a more robust conclusion.

³ This value was re-calculated for sample BDX16651 using the original data from Kreutzer et al. (2018) but excluding K-concentration values $\geq 14\%$.

Unfortunately, the degraded cooling system stopped us from carrying out additional experiments. Does this leave the question open of whether to expect hidden malign effects in the results of samples THQ and BDX16551? Our observations indicated

430 that cooling system problems were always clearly visible in the IR-RF curves, manifesting in vastly overestimated unrealistic results. An observation we did not make for the presented results.

In the absence of such technical issues, given that our method can be tested successfully at more extensive data sets, the next logical step would be to link SR IR-RF with spectral measurements. Trautmann et al. (2000) performed spectrally resolved radiofluorescence measurements of single feldspar grains. They demonstrated that the radioluminescence emission spectra,

435 could significantly differ from grain to grain. They also showed that plagioclase grains might also emit IR-RF signals and mentioned that the separation of K-feldspar grains from other feldspar grains could not be taken for granted. Nevertheless, Trautmann et al. (2000) concluded, that 'good' grains and 'bad' grains might be distinguishable by their spectral fingerprint.

In the same year, Krbetschek et al. (2000) showed that artificial irradiation could stimulate an RF emission centred at 700nm.

This additional emission may interfere with IR-RF measurements. However, for the sample BDX16651, we performed brief tests 440 with a spectrometer and did not find any indication for a potential signal interference (not shown, to be presented elsewhere).

Successive spatially resolved RF measurements at different wavelengths are possible if the measurement device deploys an automated filter wheel. In principle, it is even possible to rotate the filter wheel during one measurement and take RF images of multiple wavelengths almost simultaneously. Nevertheless, this would require a significant software update. Still, the software framework presented in this paper may provide the basis to analyse such measurements.

445 Buylaert et al. (2018) unsuccessfully searched for a correlation between K concentration and the post-IR IRSL D_e in single grains of K-feldspar. Recently, Kumar et al. (2020) reported a correlation of the K concentration and the IR signal measured with cathodoluminescence. Spatially resolved RF measurements in combination with spatially resolved IRSL measurements may help to link both observations.

5 Conclusions

450 For the first time, we outlined technique and workflow for spatially resolved infrared radiofluorescence (SR IR-RF). We presented the first measurement results, and a newly developed open-source software toolchain applicable manufacturer-independent.

In contrast to routine PMT experiments, spatially resolved measurements come with more degrees of freedom that need to be taken into account, making first steps foremost a technical challenge. Our contribution detailed relevant technical parameters,

455 of the imaging system and provided application guidelines. This will allow other laboratories to repeat our work and remove significant obstacles in applying this promising method.

Deleted: as already mentioned,

Deleted: further

Deleted: Moreover, we cannot exclude

Deleted: the two here presented cups from

Deleted: ,

Deleted: BDX16651 remained entirely

Deleted: 415 unaffected. However, our observation was

Deleted: this would be

Deleted: curve shapes, and it would potentially lead to

Deleted: could

Deleted: 420

Deleted: b

Deleted: 425

Deleted: 430

Deleted: 3

Deleted: 440

Tests on two K-feldspar samples showed results consistent with IR-RF measurements with a photomultiplier tube (PMT) for the sample TH0. However, our results also showed a large grain to grain scatter, requiring more attention and more future measurements. For the sample BDx16651, we identified up to four different D_e components, with the lowest component

460 resulting in an IR-RF age still older than the corresponding quartz age. This finding may indicate that this particular sample's bleaching time was insufficient to reset the natural IR-RF signal during sediment transport. However, if insufficient resetting has affected all K-feldspar grains, it cannot be resolved by spatially resolved measurements, but it indicates the current limit of IR-RF due to its slower signal bleachability compared to quartz.

Deleted: 445

We faced several technical issues, foremost the unstable signal background due to a camera defect. This observation demonstrates the higher complexity and potentially more error-prone technical setup than IR-RF measurements with a photomultiplier tube. Nevertheless, we are confident that more measurements using fully functional systems can exploit the presented method's full potential.

Deleted: 0

Code availability. The for this paper developed [SR-RF macro used for image processing](#), as well as a software toolchain overview and tutorials are available at <https://luminescence.de>. The R package RLumSTARR used for an automated data processing is available at [Deleted: macro](https://github.com/R-</p></div><div data-bbox=)

470 Lum/RLumSTARR. [The SR-RF macro and RLumSTARR are distributed under GPL-3 licence conditions.](#) The in this paper presented data sets as well as the used measurement sequences and analysis scripts are available at <https://doi.org/10.5281/zenodo.4395968>, and make use of [the Creative Commons license \(CC-BY-NC\)](#).

Deleted: 455

Deleted: .

Appendix A: Estimation of the signal-to-noise ratio from the camera settings

A1 Signal per pixel

475 If the signal shows no unsteadiness, inhomogeneity, non-linearity or any background signal shape, the expected signal per image pixel μ_{pixel} (in photoelectrons e^-) after background correction approximates to

Deleted: ¶
460

$$\mu_{pixel} \approx \epsilon_{exposure} n_{bin} \varphi_{pixel} \quad (A1)$$

where φ_{pixel} is the rate of luminescence-related photoelectrons generated in one CCD pixel in $e^-/px/s$. We assume that φ_{pixel} depends linearly on the actual photon flux emitted by the sample by an unknown constant. The other parameters are

480 explained and discussed in the following. Be aware that all signal and noise values in the following use the unit photoelectrons, per pixel e^- , which is not equal to the unit counts per pixel displayed in the image data. The conversion rate between photoelectrons and counts depends on multiple camera settings and is of just minor relevance for the signal-to-noise ratio (SNR) and therefore not discussed here. Be also aware that if not stated otherwise, we always refer to image pixels not CCD pixels.

Deleted: ¶
465

485 The binning factor n_{bin} expresses the number of CCD pixels combined to one image pixel. Applying pixel binning improves the signal-to-noise ratio, because the signal of the pixels is summed up, but this signal is only one time affected by readout noise. The RF optic of the *lexsyg research* system has a lateral magnification of about $M \approx 0.6$. The resulting spatial resolution is listed in Table A1 (11/2018 @L2, IRAMAT-CRP2A).

Table A1. Spatial resolution and binning factor in dependence of pixel binning

Binning	n_{bin}	Spatial resolution ($M \approx 0.6$)
none	1	$\sim 25\mu\text{m}$
2x2	4	$\sim 50\mu\text{m}$
4x4	16	$\sim 100\mu\text{m}$

The image exposure time $t_{exposure}$ (s) is user defined. It is reasonable to set the exposure time $t_{exposure}$ in dependence of 490 the measurements channel time $t_{channel}$ (s):

- Sequential readout (Full Frame Mode): $t_{exposure} = t_{channel} - t_{dead}$
- Simultaneous readout (Frame Transfer Mode): $t_{exposure} = t_{channel}$

If the camera runs in Full Frame Mode, any luminescence signal and trigger signal arriving during pixel shifting, pixel readout and data transmission will be lost. This is the case for measurements achieved with *LexStudio 2* (11/2018 @L2,

495 IRAMAT-CRP2A) and results in a recommended camera dead time t_{dead} (s). Table A2 shows tested and believed safe deadtime values. Within this time range, the camera will have finished image readout and transmission. Shorter dead times may work but likely lead to lost trigger signals and therefore lost images. If the camera runs in Frame Transfer Mode (default mode for most scientific CCD imaging systems), the image shifted into a special readout section on the CCD chip after the exposure time ended. The image can be read out while the new exposure can already begin (simultaneous readout). If the exposure time 500 is longer than the readout time (plus a little offset) no dead time is necessary.

Table A2. Left: CCD readout time as returned by the camera software representing theoretical lowest dead time values. Right: Experimentally derived upper dead time limits (recommended settings). For the measurement the amplifier was run in low noise mode and we used the default camera settings

	Readout time		Upper dead time	
	[s]		[s]	
	Binning		Binning	
Readout rate	none	2x2 4x4	none	2x2, 4x4

Deleted: ¶
470

Deleted: →x→~¶

Deleted: 475 —

Deleted: —

Deleted: dead-¶
480 time

Deleted: 485

Moved down [33]: A2-Noise per pixel¶
For each image pixel, we assume that the signal noise (σ_{pixel}) follows a normal distribution resulting from the superimposition of three independent sources:¶

Deleted: $\sigma_{pixel} = \sqrt{\sigma_{shot}^2 + \sigma_{dark}^2 + \sigma_{read}^2}$ (A2)¶
The shot noise (σ_{shot}) is caused by the random arrival of the photons and obeys Poisson statistics (Janesick, 2001). This¶
490

Moved down [34]: noise component is independent of any camera parameter setting and only a function of the expected luminescence signal given by the square root of Eq. A1.¶

Deleted: →4x4

Inserted Cells

100kHz	2.13	0.64	0.21	2.49	0.85	<u>0.38</u>
1MHz	0.29	0.08	0.03	0.47	0.24	<u>0.18</u>

A2 Noise per pixel

For each image pixel, we assume that the signal noise (σ_{pixel}) follows a normal distribution resulting from the superimposition of three independent sources:

$$\sigma_{pixel} = \sqrt{\sigma_{shot}^2 + \sigma_{dark}^2 + \sigma_{read}^2} \quad (A2)$$

505 The shot noise (σ_{shot}) is caused by the random arrival of the photons and obeys Poisson statistics (Janesick, 2001). This noise component is independent of any camera parameter setting and only a function of the expected luminescence signal given by the square root of Eq. A1.

The dark shot noise (σ_{dark}) is the shot noise of the dark current of the CCD.

$$\sigma_{dark} = \sqrt{P_{exposure} N_{bin} \phi_{dark}} \quad (A3)$$

510 The dark current signal ϕ_{dark} is one of two sources of camera-internal signal background (besides the ADC offset, which contributes no significant noise). The dark current arises mainly from thermally released charge carriers at the CCD surface and in the depletion region (Janesick, 2001). The dark shot noise is nearly exponentially dependent on the CCD temperature T_{CCD} (°C) and its value is characteristic to each individual camera (cf. Janesick, 2001).

As rule of thumb, reducing the CCD chip temperature by 10 K quarters the dark current signal and halves the dark noise.

515 The following estimation formula is derived from the *Certificate of Performance* dark charge calibration value of our camera (PI ProEM512B @L2, IRAMAT-CRP2A) and multiple specifications sheets of similar cameras:

$$\phi_{dark} \sim 210e^{0.144T_{CCD}} \quad (A4)$$

See Fig. S1 in the supplement for a plot of that equation. The dark current signal itself dissolves in the data analysis process. However, the contribution of the dark shot noise in Eq. A2 grows with the binning factor, the exposure time and especially the 520 CCD temperature. The dark shot noise of the camera used in this contribution is estimated in Table A3.

Table A3. Dark shot noise per image pixel estimation in dependence of exposure time, binning factor and CCD temperature for an average Princeton Instruments ProEM512 camera.

Moved down [35]: 0.38

Moved (insertion) [35]

Moved down [36]: 0.18

Moved (insertion) [36]

Moved (insertion) [33]

Moved (insertion) [34]

Deleted: <object>

Deleted: ¶
495

Deleted: For the sake of simplicity, we limit our discussion on the following estimation formula, derived from multiple specifications sheets of similar cameras and the *Certificate of Performance* dark charge calibration value of our specific camera (PI ProEM512B @L2, IRAMAT-CRP2A):

Deleted: 500

Deleted: 505

Moved down [37]: The readout noise σ_{read} is a result of the register readout. It is independent of the exposure time and the CCD temperature and approximately independent from pixel binning. The readout noise increases with increasing readout rate. For our camera and deploying the available traditional amplifier readout modes, readout noise values are listed in Table A4.¶

Deleted: Scientific CCD cameras of this type achieve usually a readout noise of ~ 3e- at 100kHz and ~ 5e- at 1MHz (as for 2018).¶

Deleted: ¶
Estimated dark shot noise (e-)¶
→TCCD = -70°C →TCCD = -45°C ... [4]

Estimated dark shot noise (e ⁻)						
Exposure time	T _{CCD} = -70 C			T _{CCD} = -45 C		
	Binning			Binning		
	none	2×2	4×4	none	2×2	4×4
0.5s	0.1	0.1	0.3	0.4	0.8	1.6
1s	0.1	0.2	0.4	0.6	1.1	2.3
2s	0.1	0.3	0.5	0.8	1.6	3.2
5s	0.2	0.4	0.8	1.3	2.5	5.1
10s	0.3	0.6	1.2	1.8	3.6	7.2
20s	0.4	0.8	1.7	2.5	5.1	10.2
40s	0.6	1.2	2.4	3.6	7.2	14.4

The readout noise σ_{read} is a result of the register readout. It is independent of the exposure time and the CCD temperature and approximately independent from pixel binning. The readout noise increases with increasing readout rate. For our camera and deploying the available traditional amplifier readout modes, readout noise values are listed in Table A4.

525 Scientific CCD cameras of this type achieve usually a readout noise of ~ 3e⁻ at 100kHz and ~ 5e⁻ at 1MHz (as for 2018).

Table A4. Readout noise dependence of readout rate using the traditional low noise amplifier. Values according to the *Certificate of Performance* of the PI ProEM512B camera at device L2, IRAMAT-CRP2A

Readout rate	Readout noise
	[e ⁻]
100kHz	3.3
1MHz	7.5
5MHz	14.1

The signal-to-noise ratio (SNR) is a common quality marker for measurement data. The SNR per image pixel is defined by

$$SNR_{pixel} = \frac{\mu_{pixel}}{\sigma_{pixel}}$$

(A5)

Approximations of the signal per pixel μ_{pixel} and the noise per pixel σ_{pixel} are given by Eq. A1 and Eq. A2.

A3 Signal-to-noise ratio per grain

530 In terms of image processing, a grain is defined by its region-of-interest (ROI). While the pixel SNR (Eq. A5) can help to optimise the camera settings, it does not factor the size of the ROI in. It is reasonable to set the ROI diameter about 50 % larger than

Moved (insertion) [37]

Deleted: -A3- Signal-to-noise ratio per region of interest
510

$$SNR_{pixel} = \frac{\mu_{pixel}}{\sigma_{pixel}}$$

Deleted:

Deleted: Signal

Deleted: image

Deleted: image

Deleted: can be approximated

Deleted: However, of more interest than the pixel SNR is the SNR of one grain's RF signal.

Deleted: ¶
(ROI).

the average grain diameter. With the lateral magnification known (here M = 0.6) and the CCD pixel size known (here $d_{pixel} = 16 \mu\text{m}$), the grain size can be converted into pixels and vice versa.

535 To approximate the SNR of a single grain IR-RF signal in dependence of the ROI size, we assume that the signal remains on a steady level (no decay) and that all signal light reaching the CCD is gathered in the associated ROI (no light scattering). Then, the IR-RF signal per grain (μ_{grain}) depends just on the emitted photon flux of the grain and the exposure time $t_{exposure}$.

$$\mu_{grain} = t_{exposure} \phi_{grain} \quad (A6)$$

Here, ϕ_{grain} is the signal flux per grain (in e^-/s) inside the ROI, which is proportional to the emitted photon flux. The signal per pixel μ_{pixel} (Eq. A1) for all ROI pixels add up to the signal per grain μ_{grain} . We consider the distribution of μ_{pixel} inside the ROI as unimportant.

While the grain signal μ_{grain} is independent to all parameters but the exposure time, the signal noise per grain σ_{grain} depends also on the ROI size n_{ROI} and the camera settings:

545 $\sigma_{grain} = \sqrt{\mu_{grain} + n_{ROI} \sigma_{dark}^2 + n_{ROI} \sigma_{read}^2}$ (A7) Thus, the single-grain radiofluorescence signal-to-noise ratio SNR_{grain} can be approximated by:

$$SNR_{grain} = \frac{t_{exposure} \phi_{grain}}{\sqrt{t_{exposure} \phi_{grain} + n_{ROI} t_{exposure} n_{bin} \phi_{dark} + n_{ROI} \sigma_{read}^2}} \quad (A8)$$

Here, n_{ROI} is the number of pixels in the ROI, available in the table.rf file. The signal per grain ϕ_{grain} has to be user-defined and can be considered as the same order of magnitude as the counts per second a grain would contribute to PMT

550 measurements. We defined an arbitrary dim grain and estimated SNR_{grain} for different camera settings in Table A5. We consider a SNR of at least $SNR_{grain} > 3$ as necessary to enable sufficiently precise single-grain dating.

Table A5. Decision table for best binning and channel time settings. We compare the system used in our study and a (hypothetical) similar system with comparable new camera and improved control software. Bold SNR values are related to the high SNR camera settings, recommend in Table 3.

Grain settings	lexsyg L2 IRAMAT-CRP2A	improved system
$\phi_{grain} = 20 e^- s^{-1}$	$\sigma_{read} = 3.3 e^- (7.5 e^-)$	$\sigma_{read} = 3 e^- (5 e^-)$
$d_{grain} = 160 \mu\text{m}$	$T_{CCD} = -45 C$	$T_{CCD} = -70 C$

Deleted: 515 known (here M = 0.6) and

Deleted: CCD pixel

Deleted: known (here $d_{pixel} = 16 \mu\text{m}$), measures of length can be converted into pixels and vice versa. ¶ For our SNR approximation

Deleted: grain IR-RF

Deleted: 520

Deleted: exposure time and the

Deleted: CCD

Deleted:),

Deleted: In contrast

Deleted: (

Deleted:)

Deleted: ,

Deleted: and the grain signal itself. The 525 summed-up signal noise per ROI is given by

Deleted: → ¶

Deleted: q

Deleted: (

Deleted:)

Deleted: $SNR_{grain} = \frac{t_{exposure} \phi_{grain}}{\sqrt{t_{exposure} \phi_{grain} + n_{ROI} t_{exposure} n_{bin} \phi_{dark} + n_{ROI} \sigma_{read}^2}}$

Deleted: ¶

530

Deleted: Author contributions. Dirk Mittelstraß developed the ImageJ image processing algorithm and investigated the image acquisition issue. Sebastian Kreuzer performed the measurements, provided the interface to R and investigated the signal cross-talk issue. Both authors helped 535 Freiberg Instruments to solve technical issues. Both authors jointly analysed the data and contributed equally to the manuscript. ¶

Moved (insertion) [38]

Moved (insertion) [39]

		<u>Sequential readout</u>			<u>Simultaneous readout</u>		
<u>Desired spatial resolution:</u>	<u>25μm</u>	<u>50μm</u>	<u>100μm</u>	<u>25μm</u>	<u>50μm</u>	<u>100μm</u>	
<u>Binning:</u>	<u>none</u>	<u>2\times2</u>	<u>4\times4</u>	<u>none</u>	<u>2\times2</u>	<u>4\times4</u>	
<u>ROI diameter:</u>	<u>10</u>	<u>5</u>	<u>3</u>	<u>10</u>	<u>5</u>	<u>3</u>	
<u>Desired time resolution⁴</u>	<u>Exposure time</u>	<u>Single-grain IR-RF signal-to-noise ratio</u>					
<u>2.5s</u>	<u>0.5s</u>	-	<u>0.1*</u>	<u>0.3*</u>	<u>0.2*</u>	<u>0.4*</u>	<u>1.0</u>
<u>5s</u>	<u>1s</u>	<u>0.2*</u>	<u>0.4*</u>	<u>1.1</u>	<u>0.4*</u>	<u>1.4</u>	<u>2.0</u>
<u>10s</u>	<u>2s</u>	<u>0.5*</u>	<u>1.4</u>	<u>2.3</u>	<u>0.9*</u>	<u>2.6</u>	<u>3.6</u>
<u>25s</u>	<u>5s</u>	<u>1.6</u>	<u>4.0</u>	<u>4.6</u>	<u>3.5</u>	<u>5.8</u>	<u>7.3</u>
<u>50s</u>	<u>10s</u>	<u>4.3</u>	<u>7.1</u>	<u>7.1</u>	<u>6.6</u>	<u>10.0</u>	<u>11.7</u>
<u>100s</u>	<u>20s</u>	<u>8.6</u>	<u>11.4</u>	-	<u>11.9</u>	<u>16.3</u>	-
<u>200s</u>	<u>40s</u>	<u>14.7</u>	-	-	<u>20.3</u>	-	-

555 Competing interests. The last upgrade of the IR-RF measurement system in Bordeaux was financially supported by the Freiberg Instruments GmbH. However, the manufacturer had no part in the scientific work or this manuscript. The authors declare no further competing interests.

Disclaimer. The authors developed the attached and linked software tools with great care and the reader may find them useful. However, the software comes WITHOUT ANY WARRANTY; without even the implied warranty of MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE.

560 Acknowledgements. We are grateful to three anonymous reviewers and James K. Feathers for constructive and supportive comments.

⁴ Time resolution of the processed image stack, given a Image Groupe Size of $n=5$ is parametrised.

Author contributions. Dirk Mittelstraß developed the *ImageJ* image processing algorithm and investigated the image acquisition issue. Sebastian Kreuzer performed the measurements, provided the interface to R and investigated the signal cross-talk issue. Both authors helped Freiberg Instruments to solve technical issues. Both authors jointly analysed the data and contributed equally to the manuscript.

Deleted: 540

Moved up [38]: Table A5. Decision table for best binning and channel time settings. We compare the system used in our study and a (hypothetical) similar system with comparable new camera and improved control software. Bold SNR values are related to the *high SNR* camera settings, recommend in Table 3.¶

Moved up [39]: $\varphi_{\text{grain}}=20\text{e-s}-1$

Deleted: Grain settings ... [5]

Deleted: Desired spatial resolution: ... [6]

Camille Moreau is thanked for her work in the framework of her internship at the IRAMAT-CRP2A in 2018. Ingrid Stein and Detlev Degering are thanked for safeguarding long forgotten data treasures. Chantal Tribolo and Norbert Mercier are thanked for fruitful discussions and tremendous patience while waiting for this manuscript. The authors thank the Freiberg Instruments GmbH for their support and for suffering the noise we made. [Finally, we thank Daniel Nüst for creating and maintaining this wonderful Copernicus markdown template shipped with 565 'rticles' \(Allaire et al., 2021\), which made compiling this manuscript a lot easier. This work received financial support by the LaScArBx LabEx, a programme supported](#) by the ANR - n° ANR-10-LABX-52. In 2020, while the data analysis and the manuscript were completed, SK has received funding from the European Union's Horizon 2020 research and innovation programme under the Marie Skłodowska-Curie grant agreement No 844457 (CREdit). DM took this research as private endeavour and did not receive any specific grant from funding agencies in the public, commercial, or not-for-profit sectors.

Deleted: This work received financial support by the LaScArBx LabEx, a programme supported

Deleted: 545

570 References

- Allaire, J., Xie, Y., R Foundation, Wickham, H., Journal of Statistical Software, Vaidyanathan, R., Association for Computing Machinery, Boettiger, C., Elsevier, Broman, K., Mueller, K., Quast, B., Pruim, R., Marwick, B., Wickham, C., Keyes, O., Yu, M., Emaasit, D., Onkelinx, T., Gasparini, A., Desautels, M.-A., Leutnant, D., MDPI, Taylor and Francis, Ögreden, O., Hance, D., Nüst, D., Uvesten, P., Campitelli, E., Muschelli, J., Hayes, A., Kamvar, Z. N., Ross, N., Cannoodt, R., Luguern, D., Kaplan, D. M., Kreutzer, S., Wang, S., 575 Hesselberth, J., and Dervieux, C.: rcticles: Article Formats for R Markdown, https://github.com/rstudio/rcticles_r_package_version_0.18.3_2021.
- Baril, M. R.: CCD imaging of the infra-red stimulated luminescence of feldspars, *Radiation Measurements*, 38, 81–86, <https://doi.org/10.1016/j.radmeas.2003.08.005>, 2004.
- Bortolot, V. J.: A new modular high capacity OSL reader system, *Radiation Measurements*, 32, 751–757, [https://doi.org/10.1016/S1350-4487\(00\)00038-X](https://doi.org/10.1016/S1350-4487(00)00038-X), 2000.
- Bouab, N.: Application Des Methodes de Datation Par Luminescence Optique À L'évolution Des Environnements Désertiques - Sahara Occidental (Maroc) Et Iles Canaries Orientales (Espagne) , Ph.D. thesis, Université du Québec à Montréal, <http://constellation.uqac.ca/868/1/13721974.pdf>, 2005.
- Buylaert, J. P., Újvári, G., Murray, A. S., Smedley, R. K., and Kook, M.: On the relationship between K concentration, grain size and dose in feldspar, *Radiation Measurements*, 120, 181–187, <https://doi.org/10.1016/j.radmeas.2018.06.003>, 2018.
- Bøtter-Jensen, L., Bulur, E., Duller, G. A. T., and Murray, A. S.: Advances in luminescence instrument systems, *Radiation Measurements*, 32, 523–528, [https://doi.org/10.1016/S1350-4487\(00\)00039-1](https://doi.org/10.1016/S1350-4487(00)00039-1), 2000.
- Bøtter-Jensen, L., Andersen, C. E., Duller, G. A. T., and Murray, A. S.: Developments in radiation, stimulation and observation facilities in luminescence measurements, *Radiation Measurements*, 37, 535–541, [https://doi.org/10.1016/S1350-4487\(03\)00020-9](https://doi.org/10.1016/S1350-4487(03)00020-9), 2003.
- 590 Chauhan, N., Adhyaru, P., Vaghela, H., and Singhvi, A. K.: EMCCD based luminescence imaging system for spatially resolved geochronometric and radiation dosimetric applications, *Journal of Instrumentation*, 9, P11016–P11016, <https://doi.org/10.1088/17480221/9/11/P11016>, 2014.
- Clark-Balzan, L. and Schwenninger, J.-L.: First steps toward spatially resolved OSL dating with electron multiplying charge-coupled devices (EMCCDs): System design and image analysis, *Radiation Measurements*, 47, 797–802, <https://doi.org/10.1016/j.radmeas.2012.01.018>, 2012.
- 595 Cunningham, A. and Clark-Balzan, L.: Overcoming crosstalk in luminescence images of mineral grains, *Radiation Measurements*, 106, 498–505, <https://doi.org/10.1016/j.radmeas.2017.06.004>, 2017.
- Dietze, M., Kreutzer, S., Burow, C., Fuchs, M. C., Fischer, M., and Schmidt, C.: The abanico plot: visualising chronometric data with individual standard errors, *Quaternary Geochronology*, 31, 12–18, <https://doi.org/10.1016/j.quageo.2015.09.003>, 2016.
- 600 Duller, G. A. T. and Roberts, H. M.: Seeing Snails in a New Light, *Elements*, 14, 39–43, <https://doi.org/10.2138/gselements.14.1.39>, 2018.
- Duller, G. A. T., Bøtter-Jensen, L., and Markey, B. G.: A luminescence imaging system based on a CCD camera, *Radiation Measurements*, 27, 91–99, [https://doi.org/10.1016/S1350-4487\(96\)00120-5](https://doi.org/10.1016/S1350-4487(96)00120-5), 1997.
- Duller, G. A. T., Kook, M., Stirling, R. J., Roberts, H. M., and Murray, A. S.: Spatially-resolved thermoluminescence from snail opercula using an EMCCD, *Radiation Measurements*, 81, 157–162, <https://doi.org/10.1016/j.radmeas.2015.01.014>, 2015.

Deleted: 550

Deleted: /10.1016/j.radmeas.2003.08.005, <http://www.sciencedirect.com/science/article/pii/S1350448703003056>,

Deleted: /10.1016/S13504487(00)00038-X,

Deleted: 555

Deleted: <http://constellation.uqac.ca/868/1/13721974.pdf>,

Deleted: /10.1016/j.radmeas.2018.06.003, <http://www.sciencedirect.com/science/article/pii/S1350448717308697>,

Deleted: 560

Deleted: /10.1016/S1350-4487(00)00039-1,

Deleted: /10.1016/S1350-4487(03)00020-9,

Deleted: 565

Deleted: /10.1088/17480221/9/11/P11016,

Deleted: (EMCCDs): System design and image analysis, *Radiation Measurements*, 47, 797–802, <https://doi.org/10.1016/j.radmeas.2012.01.018>, <http://linkinghub.elsevier.com/retrieve/pii/S1350448712000820>, 2012.

Deleted: 570

Deleted: /10.1016/j.radmeas.2017.06.004, <http://linkinghub.elsevier.com/retrieve/pii/S1350448717304122>,

Deleted: /10.1016/j.quageo.2015.09.003,

Deleted: /10.2138/gselements.14.1.39,

Deleted: 575

Deleted: /10.1016/S1350-4487(96)00120-5, <http://www.sciencedirect.com/science/article/pii/S1350448796001205...>,

Deleted: /10.1016/j.radmeas.2015.01.014,

605 Duller, G. A. T., Gunn, M., and Roberts, H. M.: Single grain infrared photoluminescence (IRPL) measurements of feldspars for dating, *Radiation Measurements*, 133, 106313, <https://doi.org/10.1016/j.radmeas.2020.106313>, 2020.

Dütsch, C. and Krbetschek, M. R.: New methods for a better internal ⁴⁰K dose rate determination, *Radiation Measurements*, 27, 377–381, [https://doi.org/10.1016/S1350-4487\(96\)00153-9](https://doi.org/10.1016/S1350-4487(96)00153-9), 1997.

Erfurt, G. and Krbetschek, M.: IRSAR – A single-aliquot regenerative-dose dating protocol applied to the infrared radiofluorescence (IR-RF) of coarse-grain K-feldspar, *Ancient TL*, 21, 35–42, 2003a.

Erfurt, G. and Krbetschek, M. R.: Studies on the physics of the infrared radioluminescence of potassium feldspar and on the methodology of its application to sediment dating, *Radiation Measurements*, 37, 505–510, [https://doi.org/10.1016/S1350-4487\(03\)00058-1](https://doi.org/10.1016/S1350-4487(03)00058-1), 2003b.

Ferreira, T. and Rasband, W.: ImageJ User Guide IJ 1.46r, <https://imagej.nih.gov/ij/docs/guide/146.html>, 2012.

Fitzsimmons, K. E.: Applications in Aeolian Environments, in: *Handbook of Luminescence Dating*, edited by Bateman, M. D., pp. 110–152, 615 Whittles Publishing, Dunbeath, Scotland, UK, 2019.

Frouin, M., Huot, S., Mercier, N., Lahaye, C., and Lamothe, M.: The issue of laboratory bleaching in the infrared-radiofluorescence dating method, *Radiation Measurements*, 81, 212–217, <https://doi.org/10.1016/j.radmeas.2014.12.012>, 2015.

Frouin, M., Huot, S., Kreutzer, S., Lahaye, C., Lamothe, M., Philippe, A., and Mercier, N.: An improved radiofluorescence single-aliquot regenerative dose protocol for K-feldspars, *Quaternary Geochronology*, 38, 13–24, <https://doi.org/10.1016/j.quageo.2016.11.004>, 2017.

620 Galbraith, R. F. and Roberts, R. G.: Statistical aspects of equivalent dose and error calculation and display in OSL dating: An overview and some recommendations, *Quaternary Geochronology*, 11, 1–27, <https://doi.org/10.1016/j.quageo.2012.04.020>, 2012.

Greilich, S., Glasmacher, U., and Wagner, G. x. n.: Spatially resolved detection of luminescence: a unique tool for archaeochronometry, *Naturwissenschaften*, 89, 371–375, <https://doi.org/10.1007/s00114-002-0341-z>, 2002.

Greilich, S., Glasmacher, U. A., and Wagner, G. A.: Optical dating of granitic stone surfaces, *Archaeometry*, 47, 645–665, 625 <https://doi.org/10.1111/j.1475-4754.2005.00224.x>, 2005.

Greilich, S., Harney, H.-L., Woda, C., and Wagner, G. A.: AgesGalore—A software program for evaluating spatially resolved luminescence data, *Radiation Measurements*, 41, 726–735, <https://doi.org/10.1016/j.radmeas.2005.12.007>, 2006.

Greilich, S., Gribenski, N., Mittelstraß, D., Dornich, K., Huot, S., and Preusser, F.: Single-grain dose-distribution measurements by optically stimulated luminescence using an integrated EMCCD-based system, *Quaternary Geochronology*, 29, 70–79, 630 <https://doi.org/10.1016/j.quageo.2015.06.009>, 2015.

Gribenski, N., Preusser, F., Greilich, S., Huot, S., and Mittelstraß, D.: Investigation of cross talk in single grain luminescence measurements using an EMCCD camera, *Radiation Measurements*, 81, 163–170, <https://doi.org/10.1016/j.radmeas.2015.01.017>, 2015.

Guérin, G., Christophe, C., Philippe, A., Murray, A. S., Thomsen, K. J., Tribolo, C., Urbanova, P., Jain, M., Guibert, P., Mercier, N., Kreutzer, S., and Lahaye, C.: Absorbed dose, equivalent dose, measured dose rates, and implications for OSL age estimates: Introducing the Average Dose Model, *Quaternary Geochronology*, 41, 1–32, <https://doi.org/10.1016/j.quageo.2017.04.002>, 2017.

Gusarov, A., Doyle, D., Glebov, L., and Berghmans, F.: Comparison of radiation-induced transmission degradation of borosilicate crown optical glass from four different manufacturers, in: *Optics & Photonics 2005*, edited by Taylor, E. W., pp. 58970I–8, SPIE, <https://doi.org/10.1117/12.619199>, 2005.

Deleted: 580

Deleted: /10.1016/j.radmeas.2020.106313,

Deleted: /10.1016/S1350-4487(03)00058-1, <http://www.585sciencedirect.com/science/article/pii/S1350448703000581>,

Deleted: <https://imagej.nih.gov/ij/docs/guide/146.html>,

Deleted: 590 method, *Radiation Measurements*, 81, 212–217, <https://doi.org/10.1016/j.radmeas.2014.12.012>, <http://linkinghub.elsevier.com/retrieve/pii/S1350448715000530>, 2015.¶

Deleted: /10.1016/j.quageo.2016.11.004, <http://linkinghub.elsevier.com/retrieve/pii/S1871101416301704>,

Deleted: 595

Deleted: some recommendations, *Quaternary Geochronology*, 11, 1–27, <https://doi.org/10.1016/j.quageo.2012.04.020>, 2012.

Deleted: /10.1007/s00114-002-0341-z,

Deleted: 600 <https://doi.org/10.1111/j.1475-4754.2005.00224.x>, <https://onlinelibrary.wiley.com/doi/abs/10.1111/j.1475-4754.2005.00224.x>,

Deleted: /10.1016/j.radmeas.2005.12.007, <http://adsabs.harvard.edu/abs/2006RadM...41..726G>,

Deleted: measure-¶
605 ments

Deleted: <https://doi.org/10.1016/j.quageo.2015.06.009>, <http://linkinghub.elsevier.com/retrieve/pii/S1871101415300455>,

Deleted: /10.1016/j.radmeas.2015.01.017, <http://linkinghub.elsevier.com/retrieve/pii/S1350448715000256>,

Deleted: 610

Deleted: /10.1016/j.quageo.2017.04.002,

Huntley, D. J. and Baril, M. R.: The K content of the K-feldspars being measured in optical dating or in the thermoluminescence dating, [640](http://ancienttl.org/ATL_15-1_1997/ATL_15-1_Huntley_p11-13.pdf) Ancient TL, 15, 11–13, http://ancienttl.org/ATL_15-1_1997/ATL_15-1_Huntley_p11-13.pdf, 1997.

Huntley, D. J. and Kirkley, J. J.: The use of an image intensifier to study the TL intensity variability of individual grains, Ancient TL, pp. 1–4, 1985.

Huntley, D. J., Godfrey-Smith, D. I., and Thewalt, M. L. W.: Optical dating of sediments, Nature, 313, 105–107, <https://doi.org/10.1038/313105a0>, 1985.

[645](https://doi.org/10.1038/313105a0) Janesick, J. R.: Scientific charge-coupled devices, vol. PM83, SPIE Press Book, 2001.

Kook, M., Lapp, T., Murray, A., Thomsen, K., and Jain, M.: A luminescence imaging system for the routine measurement of single-grain OSL dose distributions, Radiation Measurements, 81, 171–177, <https://doi.org/10.1016/j.radmeas.2015.02.010>, 2015.

Krbetschek, M. R. and Degering, D.: Spatially resolved Infrared- Radiofluorescence (IR-RF) Dating - on single feldspar grains, in: 11th International LED Cologne. Oral presentation, pp. 1–24, 2005.

[650](https://doi.org/10.1016/S1350-4487(00)00122-0) Krbetschek, M. R., Trautmann, T., Dietrich, A., and Stolz, W.: Radioluminescence dating of sediments: methodological aspects, Radiation Measurements, 32, 493–498, [https://doi.org/10.1016/S1350-4487\(00\)00122-0](https://doi.org/10.1016/S1350-4487(00)00122-0), 2000.

Kreutzer, S. and Mittelstrass, D.: RLumSTARR: Spatially Resolved Radiofluorescence Analysis, <https://github.com/R-Lum/RLumSTARR>, R package version 0.1.0.9000-49, 2020a.

Kreutzer, S. and Mittelstrass, D.: Spatially Resolved Infrared Radiofluorescence (SR IR-RF) Image Data, [655](https://doi.org/10.5281/zenodo.4395968) <https://doi.org/10.5281/zenodo.4395968>, 2020b.

Kreutzer, S., Schmidt, C., Fuchs, M. C., Dietze, M., Fischer, M., and Fuchs, M.: Introducing an R package for luminescence dating analysis, Ancient TL, 30, 1–8, http://ancienttl.org/ATL_30-1_2012/ATL_30-1_Kreutzer_p1-8.pdf, 2012.

Kreutzer, S., Murari, M. K., Frouin, M., Fuchs, M., and Mercier, N.: Always remain suspicious: a case study on tracking down a technical artefact while measuring IR-RF, Ancient TL, 35, 20–30, http://ancienttl.org/ATL_35-1_2017/ATL_35-1_Kreutzer_p20-30.pdf, 2017.

[660](https://doi.org/10.1016/j.j.quageo.2018.09.005) Kreutzer, S., Duval, M., Bartz, M., Bertran, P., Bosq, M., Eynaud, F., Verdin, F., and Mercier, N.: Deciphering long-term coastal dynamics using IR-RF and ESR dating: A case study from Médoc, south-West France, Quaternary Geochronology, 48, 108–120, <https://doi.org/10.1016/j.j.quageo.2018.09.005>, 2018.

Kreutzer, S., Burow, C., Dietze, M., Fuchs, M. C., Schmidt, C., Fischer, M., Friedrich, J., Riedesel, S., Autzen, M., and Mittelstrass, D.: [Luminescence: Comprehensive Luminescence Dating Data Analysis](https://CRAN.R-project.org/package=Luminescence), <https://CRAN.R-project.org/package=Luminescence>, R package [665](https://CRAN.R-project.org/package=Luminescence) version 0.9.9, 2020.

Kumar, R., Martin, L. I. D. J., Poelman, D., Vandenbergh, D., De Grave, J., Kook, M., and Jain, M.: Site-selective mapping of metastable states using electron-beam induced luminescence microscopy, Scientific Reports, 10, 1270–14, <https://doi.org/10.1038/s41598-02072334-7>, 2020.

Liritzis, Y. and Galloway, R. B.: Bremsstrahlung from a shielded beta irradiator, Journal of Radioanalytical and Nuclear Chemistry, 146, [670](https://doi.org/10.1007/BF02164236) 333–345, <https://doi.org/10.1007/BF02164236>, 1990.

Maraba, D. and Bulur, E.: Design and construction of an automated OSL reader with open source software and hardware, Radiation Measurements, 106, 1–25, <https://doi.org/10.1016/j.radmeas.2017.04.011>, 2017.

Mauz, B., Martin, L., Discher, M., Tribolo, C., Kreutzer, S., Bahl, C., Lang, A., and Mercier, N.: Technical note: On the reliability of laboratory beta-source calibration for luminescence dating, Geochronology Discussions, 2020, 1–15, <https://doi.org/10.5194/gchron-2020-36>,

Deleted: http://ancienttl.org/ATL_15-1_1997/ATL_15-1_Huntley_p11-13.pdf,

Deleted: 615

Deleted: /10.1038/313105a0,

Deleted: 620

Deleted: /10.1016/j.radmeas.2015.02.010, <http://linkinghub.elsevier.com/retrieve/pii/S1350448715000372>,

Deleted: 2

Deleted: /10.1016/S1350-4487(00)00122-0, 2000a

Deleted: Krbetschek, M. R., Trautmann, T., Dietrich, A., and Stolz, W.: Radioluminescence dating of sediments: methodological aspects, Radiation Measurements, 32, 493–498, [https://doi.org/10.1016/S1350-4487\(00\)00122-0](https://doi.org/10.1016/S1350-4487(00)00122-0), <http://www.sciencedirect.com/science/article/pii/S1350448700001220>, 2000b. ¶

Deleted: <https://github.com/R-Lum/RLumSTARR>,

Deleted: /10.5281/zenodo.4395968, <https://doi.org/10.5281/zenodo.4395968>,

Deleted: 635

Deleted: http://ancienttl.org/ATL_30-1_2012/ATL_30-1_Kreutzer_p1-8.pdf,

Deleted: http://ancienttl.org/ATL_35-1_2017/ATL_35-1_Kreutzer_p20-30.pdf,

Deleted: 640 <https://doi.org/10.1016/j.j.quageo.2018.09.005>, 2018.

Deleted: Luminescence: Comprehensive Luminescence Dating Data Analysis, <https://CRAN.R-project.org/package=Luminescence>, R package version 0.9.9, 2020.

Deleted: ¶ 645

Deleted: /10.1038/s41598-02072334-7,

Deleted: /10.1007/BF02164236, <https://doi.org/10.1007/BF02164236>,

Deleted: Mea650 surements

Deleted: /10.1016/j.radmeas.2017.04.011,

Deleted: /10.5194/gchron-2020-36, <https://gchron.copernicus.org/preprints/gchron-2020-36/>, 2020....

675 2020.

Murari, K. M., Kreutzer, S., King, G., Frouin, M., Tsukamoto, S., Schmidt, C., Lauer, T., Klasen, N., Richter, D., Friedrich, J., Mercier, N., and Fuchs, M.: Infrared Radiofluorescence (IR-RF), Quaternary Geochronology, [64, 101155](https://doi.org/10.1016/j.quageo.2021.101155), <https://doi.org/10.1016/j.quageo.2021.101155>, 2021.

Murari, M. K., Kreutzer, S., and Fuchs, M.: Further investigations on IR-RF: Dose recovery and correction, Radiation Measurements, [120, 110–119](https://doi.org/10.1016/j.radmeas.2018.04.017), <https://doi.org/10.1016/j.radmeas.2018.04.017>, 2018.

R Core Team: R: A Language and Environment for Statistical Computing, Vienna, Austria, <https://r-project.org>, 2020.

Rhodus, C., Kadereit, A., Siegel, U., Schmidt, K., Eichmann, R., and Khalil, L. A.: Constraining the time of construction of the irrigation system of Tell Hujayrat al-Ghuzlan near Aqaba, Jordan, using high-resolution optically stimulated luminescence (HR-OSL) dating, Archaeological and Anthropological Sciences, [9, 345–370](https://doi.org/10.1007/s12520-015-0284-x), <https://doi.org/10.1007/s12520-015-0284-x>, 2015.

685 Richter, D., Pintaske, R., Dornich, K., and Krbetschek, M. R.: A novel beta source design for uniform irradiation in dosimetric applications, Ancient TL, [30, 57–63](http://ancienttl.org/ATL_30-2_2012/ATL_30-2_Richter_p57-64.pdf), http://ancienttl.org/ATL_30-2_2012/ATL_30-2_Richter_p57-64.pdf, 2012.

Richter, D., Richter, A., and Dornich, K.: lexsyg — a new system for luminescence research, Geochronometria, [40, 220–228](https://doi.org/10.2478/s13386-013-0110-0), <https://doi.org/10.2478/s13386-013-0110-0>, 2013.

Richter, D., Richter, A., and Dornich, K.: Lexsyg smart — a luminescence detection system for dosimetry, material research and dating application, Geochronometria, [42, 202–209](https://doi.org/10.1515/geochr-2015-0022), <https://doi.org/10.1515/geochr-2015-0022>, 2015.

Schneider, C. A., Rasband, W. S., and Eliceiri, K. W.: NIH Image to ImageJ: 25 years of image analysis, Nature Methods, [9, 671–675](https://doi.org/10.1038/nmeth.2089), <https://doi.org/10.1038/nmeth.2089>, 2012.

Spooner, N. A.: A photon-counting imaging system (PCIS) for luminescence applications, Radiation Measurements, [32, 513–521](https://doi.org/10.1016/S1350-4487(00)00056-1), [https://doi.org/10.1016/S1350-4487\(00\)00056-1](https://doi.org/10.1016/S1350-4487(00)00056-1), 2000.

695 Thévenaz, P., Ruttimann, U. E., and Unser, M.: A pyramid approach to subpixel registration based on intensity, IEEE transactions on image processing: a publication of the IEEE Signal Processing Society, [7, 27–41](https://doi.org/10.1109/83.650848), <https://doi.org/10.1109/83.650848>, 1998.

Trautmann, T., Krbetschek, M. R., Dietrich, A., and Stolz, W.: Investigations of feldspar radioluminescence: potential for a new dating technique, Radiation Measurements, [29, 421–425](https://doi.org/10.1016/S1350-4487(98)00012-2), [https://doi.org/10.1016/S1350-4487\(98\)00012-2](https://doi.org/10.1016/S1350-4487(98)00012-2), 1998.

Trautmann, T., Krbetschek, M., Dietrich, A., and Stolz, W.: Feldspar radioluminescence: a new dating method and its physical background, Journal of Luminescence, [85, 45–58](https://doi.org/10.1016/S0022-2313(99)00152-0), [https://doi.org/10.1016/S0022-2313\(99\)00152-0](https://doi.org/10.1016/S0022-2313(99)00152-0), 1999.

Trautmann, T., Krbetschek, M. R., and Stolz, W.: A systematic study of the radioluminescence properties of single feldspar grains, Radiation Measurements, [32, 685–690](https://doi.org/10.1016/S1350-4487(00)00077-9), [https://doi.org/10.1016/S1350-4487\(00\)00077-9](https://doi.org/10.1016/S1350-4487(00)00077-9), 2000.

Velleman, P. F.: Definition and Comparison of Robust Nonlinear Data Smoothing Algorithms, Journal of the American Statistical Association, [75, 609–615](https://doi.org/10.2307/2287657), <https://doi.org/10.2307/2287657>, 1980.

705 Wagner, G. A., Krbetschek, M. R., Degering, D., Bahain, J. J., Shao, Q., Falguères, C., Voinchet, P., Dolo, J. M., Garcia, T., and Rightmire, G. P.: Radiometric dating of the type-site for Homo heidelbergensis at Mauer, Germany, Proceedings of the National Academy of Sciences, [107, 19726–19730](https://doi.org/10.1073/pnas.1012722107), <https://doi.org/10.1073/pnas.1012722107>, 2010.

Deleted: 655

Deleted: pp. 1–53, submitted

Deleted: /10.1016/j.radmeas.2018.04.017, <https://linkinghub.elsevier.com/retrieve/pii/S1350448717307850>,

Deleted: <https://r-project.org>,

Deleted: irriga-
660 tion

Deleted: /10.1007/s12520-015-0284-x,

Deleted: http://ancienttl.org/ATL_30-2_2012/ATL_30-2_Richter_p57-64.pdf,

Deleted: 665 <https://doi.org/10.2478/s13386-013-0110-0>, 2013.

Deleted: /10.1515/geochr-2015-0022,

Deleted: <https://doi.org/10.1038/nmeth.2089>, <http://www.nature.com/doifinder/10.1038/nmeth.2089>, 2012.

Deleted: 670

Deleted: /10.1016/S1350-4487(00)00056-1, <http://www.sciencedirect.com/science/article/pii/S1350448700000561>,

Deleted: /10.1109/83.650848,

Deleted: 675

Deleted: /10.1016/S1350-4487(98)00012-2,

Deleted: /10.1016/S0022-2313(99)00152-0, <http://linkinghub.elsevier.com/retrieve/pii/S0022231399001520>,

Deleted: Ra-

Deleted: 680 diation Measurements, [32, 685–690](https://doi.org/10.1016/S1350-4487(00)00077-9), [https://doi.org/10.1016/S1350-4487\(00\)00077-9](https://doi.org/10.1016/S1350-4487(00)00077-9), <http://www.sciencedirect.com/science/article/pii/S1350448700000779>, 2000.

Deleted: /10.2307/2287657, <https://www.jstor.org/stable/2287657>,

Deleted:
685

Deleted: /10.1073/pnas.1012722107,

Page 14: [1] Deleted	Authors	30/03/2021 14:34:00
Page 14: [2] Deleted	Authors	30/03/2021 14:34:00
Page 14: [3] Deleted	Authors	30/03/2021 14:34:00
Page 27: [4] Deleted	Authors	30/03/2021 14:34:00
Page 30: [5] Deleted	Authors	30/03/2021 14:34:00
Page 30: [6] Deleted	Authors	30/03/2021 14:34:00